

Wavelet Analysis of Variance for Time Series with Missing Values

Debashis Mondal¹ and Donald B. Percival²

Technical Report no. 535

Department of Statistics, University of Washington

Abstract

The wavelet variance is a scale-based decomposition of the process variance for a time series and has been used to analyze, for example, time deviations in atomic clocks, variations in soil properties in agricultural plots, accumulation of snow fields in the polar regions and marine atmospheric boundary layer turbulence. We propose two new unbiased estimators of the wavelet variance when the observed time series is ‘gappy,’ i.e., is sampled at regular intervals, but certain observations are missing. We deduce the large sample properties of these estimators and discuss methods for determining an approximate confidence interval for the wavelet variance. We apply our proposed methodology to series of gappy observations related to atmospheric pressure data and Nile River minima.

Key words: Cumulant; Fractionally differenced process; Local stationarity; Nile River minima; Semi-variogram; TAO data.

1 Introduction

In recent years, there has been great interest in using wavelets to analyze data arising from various scientific fields. The pioneering work of Donoho, Johnstone and co-workers on wavelet shrinkage sparked this interest, and wavelet methods have been used to study a large number of problems in signal and image processing including density estimation, deconvolution, edge detection, nonparametric regression and smooth estimation of evolutionary spectra. See, for example, Candès and Donoho (2002), Donoho et al. (1995), Donoho and Johnstone (1998), Genovese and Wasserman (2005), Hall and Penev (2004), Kalifa and Mallat (2003), Neumann and von Sachs (1997) and references therein. Wavelets also give rise to the concept of the wavelet variance (also called the wavelet power spectrum), which decomposes the sample variance of a time series on a scale by scale basis and provides a time- and scale-based analysis of variance. Here ‘scale’ refers to a fixed interval or span of time (Percival, 1995). The wavelet variance is particularly useful as an exploratory tool to identify important scales, to assess

¹Department of Statistics, University of Chicago

²Applied Physics Laboratory and Department of Statistics, University of Washington

properties of long memory processes, to detect inhomogeneity of variance in time series and to estimate time-varying power spectra (thus complementing classical Fourier analysis). Applications include the analysis of time series related to electroencephalographic sleep state patterns of infants (Chiann and Morettin, 1998), the El Niño–Southern Oscillation (Torrence and Compo, 1998), soil variations (Lark and Webster, 2001), solar coronal activity (Rybák and Dorotovič, 2002), the relationship between rainfall and runoff (Labat et al., 2001), ocean surface waves (Massel, 2001), surface albedo and temperature in desert grassland (Pelgrum et al., 2000), heart rate variability (Pichot et al., 1999) and the stability of the time kept by atomic clocks (Greenhall et al, 1999).

1.1 Variance decomposition

If X_t ($t \in \mathcal{Z}$) is a second-order stationary process, a fundamental property of the wavelet variance is that it breaks up the process variance into pieces, each of which represents the contribution to the overall variance due to variability on a particular scale. In mathematical notation,

$$\text{var}(X_t) = \sum_{j=1}^{\infty} \nu_X^2(\tau_j),$$

where $\nu_X^2(\tau_j)$ is the wavelet variance associated with dyadic scale $\tau_j = 2^{j-1}$; see equation (5) for the precise definition. Roughly speaking, $\nu_X^2(\tau_j)$ is a measure of how much a weighted average of X_t over an interval of τ_j differs from a similar average in an adjacent interval. A plot of $\nu_X^2(\tau_j)$ against τ_j thus reveals which scales are important contributors to the process variance. The wavelet variance is also well-defined if X_t is intrinsically stationary, which means that X_t is nonstationary but its backward differences of a certain order d are stationary. For such a process the wavelet variance at individual scales τ_j exists and serves as a meaningful description of variability of the process.

1.2 Scalegram

If X_t is intrinsically stationary and has an associated spectral density function (SDF) S_X , the wavelet variance provides a simple regularization of S_X in the sense that

$$\nu_X^2(\tau_j) \approx 2 \int_{2^{-j-1}}^{2^{-j}} S_X(f) df.$$

The wavelet variance thus summarizes the information in the SDF using just one value per octave band $f \in [2^{-j-1}, 2^{-j}]$ and is particularly useful when the SDF is relatively featureless within each octave band. Suppose for example that X_t is a pure power law process, which means that its SDF is proportional to $|f|^\alpha$. Then, with a suitable choice of the wavelet filter, $\nu_X^2(\tau_j)$ is approximately proportional to $\tau_j^{-\alpha-1}$. The scalegram is a plot of $\log\{\nu_X^2(\tau_j)\}$ versus $\log(\tau_j)$. If it is approximately linear, a power law process is indicated, and the exponent α of the power law can be determined from the slope of the line. Thus for this and other simple models there is no loss in using the summary given by the wavelet variance.

1.3 Local Stationarity

Wavelet analysis is particularly useful to handle data that exhibit inhomogeneities. For example if the assumption of stationarity is in question, an alternative assumption is that the time series is locally stationary and can be divided into homogenous blocks (see Section 7.2 for an example of a time series for which the homogeneity assumption is questionable). The wavelet variance can be used to check the need for this more complicated approach. Moreover, when stationarity is questionable, as an alternative to dividing the time series into disjoint blocks, we can compute wavelet power spectra within a data window and compare its values as the window slides through the time series. The typical situation is geophysics is that more observations are collected with the passage of time rather than by, e.g., sampling more finely over a fixed finite interval, so we do not consider procedures where more data are entertained via an in-fill mechanism.

1.4 Gappy series

In practice, time series collected in various fields often deviate from regular sampling by having missing values ('gaps') amongst otherwise regularly sampled observations. As is also the case with the classical Fourier transform, the usual discrete wavelet transform is designed for regularly sampled observations and cannot be applied directly to time series with gaps. In geophysics, gaps are often handled by interpolating the data, see e.g., Vio et al. (2000), but such schemes are faced with the problem of bias and of deducing what effect interpolation has had on any resulting statistical inference. There are various definitions for nonstandard wavelet transforms that could be applied to gappy data, with the 'lifting' scheme being a prominent example (Sweldens, 1997). The general problem with this approach is that the wavelet coefficients are not truly associated with particular scales of interest, thus making it hard to draw meaningful scale-dependent inferences. The methodologies developed here overcome these problems. Wavelet analysis has also been discussed in the context of irregular time series (Foster, 1996), and in the context of signals with continuous gaps (Frick and Tchamitchian, 1998). Related works address the problem of the spectral analysis of gappy data (Stoica et al., 2000). The statistical properties of some of these methodologies are unknown and not easy to derive. We return to this in Section 8 and indicate how we can use our wavelet variance estimator to estimate the SDF for gappy data.

This paper is laid out as follows. In Section 2 we discuss estimation of the wavelet variance for gap-free time series. In Section 3 and 4 we describe estimation and construction of confidence intervals for the wavelet variance based upon gappy time series. In Section 5 we compare various estimates and perform some simulation studies on autoregressive and fractionally differenced processes, while Section 6 describes schemes for estimating wavelet variance for time series with stationary d th order backward differences. We consider two examples involving gappy time series related to atmospheric pressure and Nile River minima in Section 7. Finally we end with some discussion in Section 8.

2 Wavelet variance estimation for non-gappy time series

Let $h_{1,l}$ denote a unit level Daubechies wavelet filter of width L normalized such that $\sum_l h_{1,l}^2 = \frac{1}{2}$ (Daubechies, 1992). The transfer function for this filter, i.e., its discrete Fourier transform (DFT)

$$H_1(f) = \sum_{l=0}^{L-1} h_{1,l} e^{-i2\pi f l},$$

has a corresponding squared gain function by definition satisfying

$$\mathcal{H}_1(f) \equiv |H_1(f)|^2 = \sin^L(\pi f) \sum_{l=0}^{\frac{L}{2}-1} \binom{\frac{L}{2}-1+l}{l} \cos^{2l}(\pi f). \quad (1)$$

We note that $h_{1,l}$ can be expressed as the convolution of $\frac{L}{2}$ first difference filters and a single averaging filter that can be obtained by performing $\frac{L}{2}$ cumulative summations on $h_{1,l}$. The j th level wavelet filter $h_{j,l}$ is defined as the inverse DFT of

$$H_j(f) = H_1(2^{j-1}f) \prod_{l=0}^{j-2} e^{-i2\pi 2^l f(L-1)} H_1(\frac{1}{2} - 2^l f). \quad (2)$$

The width of this filter is given by $L_j \equiv (2^j - 1)(L - 1) + 1$. We denote the corresponding squared gain function by \mathcal{H}_j . Since $H_j(0) = 0$, it follows that

$$\sum_{l=0}^{L_j-1} h_{j,l} = 0. \quad (3)$$

For a nonnegative integer d , let X_t ($t \in \mathcal{Z}$) be a process with d th order stationary increments, which implies that

$$Y_t \equiv \sum_{k=0}^d \binom{d}{k} (-1)^k X_{t-k} \quad (4)$$

is a stationary process. Let S_X and S_Y represent the SDFs for X_t and Y_t . These SDFs are defined over the Fourier frequencies $f \in [-\frac{1}{2}, \frac{1}{2}]$ and are related by $S_Y(f) = [2 \sin(\pi f)]^{2d} S_X(f)$. We can take the wavelet variance at scale $\tau_j = 2^{j-1}$ to be defined as

$$\nu_X^2(\tau_j) \equiv \int_{-1/2}^{1/2} \mathcal{H}_j(f) S_X(f) df. \quad (5)$$

By virtue of (1) and (2), the wavelet variance is well defined for $L \geq 2d$. When $d = 0$ so that X_t is a stationary process with autocovariance sequence (ACVS) $s_{X,k} \equiv \text{cov}\{X_t, X_{t+k}\}$, then we can rewrite the above as

$$\nu_X^2(\tau_j) = \sum_{l=0}^{L_j-1} \sum_{l'=0}^{L_j-1} h_{j,l} h_{j,l'} s_{X,l-l'}. \quad (6)$$

When $d = 1$, the increment process $Y_t = X_t - X_{t-1}$ rather than X_t itself is stationary, in which case the above equation can be replaced by one involving the ACVS for Y_t and the cumulative sum of $h_{j,l}$ (Craigmle and Percival, 2005). Alternatively, let $\gamma_{X,k} = \frac{1}{2}\text{var}(X_0 - X_k)$ denote the semi-variogram of X_t . Then the wavelet variance can be expressed as

$$\nu_X^2(\tau_j) = - \sum_{l=0}^{L_j-1} \sum_{l'=0}^{L_j-1} h_{j,l} h_{j,l'} \gamma_{X,l-l'}. \quad (7)$$

The above equation also holds when X_t is stationary.

Given an observed time series that can be regarded as a realization of X_0, \dots, X_{N-1} and assuming the sufficient condition $L > 2d$, an unbiased estimator of $\nu_X^2(\tau_j)$ is given by

$$\hat{\nu}_X^2(\tau_j) \equiv \frac{1}{M_j} \sum_{t=L_j-1}^{N-1} W_{j,t}^2,$$

where $M_j \equiv N - L_j + 1$, and

$$W_{j,t} \equiv \sum_{l=0}^{L_j-1} h_{j,l} X_{t-l}.$$

The wavelet coefficient process $W_{j,t}$ is stationary with mean zero, an SDF given by $\mathcal{H}_j(f)S_X(f)$ and an ACVS to be denoted by $s_{j,k}$. The following theorem holds (Percival, 1995).

Theorem 1 *Let $W_{j,t}$ be a mean zero Gaussian stationary process satisfying the square integrable condition*

$$A_j \equiv \int_{-1/2}^{1/2} \mathcal{H}_j^2(f) S_X^2(f) df = \sum_{k=-\infty}^{\infty} s_{j,k}^2 < \infty.$$

Then $\hat{\nu}_X^2(\tau_j)$ is asymptotically normal with mean $\nu_X^2(\tau_j)$ and large sample variance $2A_j/M_j$.

In practical applications, A_j is estimated by

$$\hat{A}_j = \frac{1}{2} \hat{s}_{j,0}^2 + \sum_{k=1}^{M_j-1} \hat{s}_{j,k}^2,$$

where

$$\hat{s}_{j,k} = \frac{1}{M_j} \sum_{t=L_j-1}^{N-1-|k|} W_{j,t} W_{j,t+|k|}$$

is the usual biased estimator of the ACVS for a process whose mean is known to be zero. Theorem 1 provides a simple basis for constructing confidence intervals for the wavelet variance $\nu_X^2(\tau_j)$.

3 Wavelet variance estimation for gappy time series

We consider first the case $d = 0$, so that X_t itself is stationary with ACVS $s_{X,k}$ and variogram $\gamma_{X,k}$. Consider a portion X_0, \dots, X_{N-1} of this process. Let δ_t be the corresponding gap pattern, assumed to be a portion of a binary stationary process independent of X_t . The random variable δ_t assumes the values of 0 or 1 with nonzero probabilities, with zero indicating that the corresponding realization for X_t is missing. Define

$$\beta_k^{-1} = \Pr(\delta_t = 1 \text{ and } \delta_{t+k} = 1),$$

which is necessarily greater than zero. For $0 \leq l, l' \leq L_j - 1$, let

$$\hat{\beta}_{l,l'}^{-1} \equiv \frac{1}{M_j} \sum_{t=L_j-1}^{N-1} \delta_{t-l} \delta_{t-l'}.$$

We assume that $\hat{\beta}_{l,l'}^{-1} > 0$ for all l and l' . For a fixed j , this condition will hold asymptotically almost surely, but it can fail for finite N for a time series with too many gaps, a point that we return to in Section 8. By the weak law of large number for dependent processes (Felle 1966, p. 240, ex. 9), $\hat{\beta}_{l,l'}^{-1}$ is a consistent estimator of $\beta_{l-l'}^{-1}$ as $N \rightarrow \infty$.

Consider the following two statistics:

$$\hat{u}_X(\tau_j) \equiv \frac{1}{M_j} \sum_{t=L_j-1}^{N-1} \sum_{l=0}^{L_j-1} \sum_{l'=0}^{L_j-1} h_{j,l} h_{j,l'} \hat{\beta}_{l,l'}^{-1} X_{t-l} X_{t-l'} \delta_{t-l} \delta_{t-l'} \quad (8)$$

and

$$\hat{v}_X(\tau_j) \equiv -\frac{1}{2M_j} \sum_{t=L_j-1}^{N-1} \sum_{l=0}^{L_j-1} \sum_{l'=0}^{L_j-1} h_{j,l} h_{j,l'} \hat{\beta}_{l,l'}^{-1} (X_{t-l} - X_{t-l'})^2 \delta_{t-l} \delta_{t-l'}. \quad (9)$$

When $\delta_t = 1$ for all t (the gap-free case), both statistics collapse to $\hat{\nu}_X^2(\tau_j)$. Conditioning on the observed gap pattern $\delta = (\delta_0, \dots, \delta_{N-1})$, it follows that

$$E\{\hat{u}_X(\tau_j) \mid \delta\} = E\{\hat{v}_X(\tau_j) \mid \delta\} = \nu_X^2(\tau_j)$$

and hence that both statistics are unconditionally unbiased estimators of $\nu_X^2(\tau_j)$; however, whereas $\hat{\nu}_X^2(\tau_j) \geq 0$ necessarily in the gap-free case, these two estimators can be negative.

Remark 2 *In the gappy case, the covariance type estimator $\hat{u}_X(\tau_j)$ does not remain invariant if we add a constant to the original process X_t , whereas the variogram type estimator $\hat{v}_X(\tau_j)$ does. In practical applications, this fact becomes important if the sample mean of the time series is large compared to its sample standard deviation, in which case it is important to use $\hat{u}_X(\tau_j)$ only after centering the series by subtracting off the sample mean.*

4 Large sample properties of $\hat{u}_X(\tau_j)$ and $\hat{v}_X(\tau_j)$

For a fixed j , define the following stochastic processes:

$$Z_{u,j,t} \equiv \sum_{l=0}^{L_j-1} \sum_{l'=0}^{L_j-1} h_{j,l} h_{j,l'} \beta_{l-l'} X_{t-l} X_{t-l'} \delta_{t-l} \delta_{t-l'}, \quad (10)$$

and

$$Z_{v,j,t} \equiv -\frac{1}{2} \sum_{l=0}^{L_j-1} \sum_{l'=0}^{L_j-1} h_{j,l} h_{j,l'} \beta_{l-l'} (X_{t-l} - X_{t-l'})^2 \delta_{t-l} \delta_{t-l'}. \quad (11)$$

The processes $Z_{u,j,t}$ and $Z_{v,j,t}$ are both stationary with mean $\nu_X^2(\tau_j)$, and both collapse to $W_{j,t}^2$ in the gap-free case. Our estimators $\hat{u}_X(\tau_j)$ and $\hat{v}_X(\tau_j)$ are essentially sample means of $Z_{u,j,t}$ or $Z_{v,j,t}$, with $\beta_{l-l'}$ replaced by $\hat{\beta}_{l,l'}$. At this point we assume the following technical condition about our gap process.

Assumption 3 For fixed j , let $V_{p,t} = \delta_{t-l} \delta_{t-l'}$ for $p = (l, l')$ and $l, l' = 0, \dots, L_j - 1$. We assume that the covariances of $V_{p_1,t}$ and $V_{p_2,t}$ are absolutely summable and the higher order cumulants satisfy

$$\sum_{t_1=0}^{N-1} \cdots \sum_{t_n=0}^{N-1} |\text{cum}(V_{p_1,t_1}, \dots, V_{p_n,t_n})| = o(N^{n/2}) \quad (12)$$

for $n = 3, 4, \dots$ and for fixed p_1, \dots, p_n .

Remark 4 Assumption 3 holds for a wide range of binary processes. For example, if δ_t is derived by thresholding a stationary Gaussian process whose covariances are absolutely summable, then the higher order cumulants of $V_{p,t}$ are absolutely summable. Note that Assumption 3 is weaker than the assumption that the cumulants are absolutely summable. This latter assumption has been used to prove central limit theorems in other contexts; see, e.g., Assumption 2.6.1 of Brillinger (1981).

The following central limit theorems (Theorem 5 and 7) provide the basis for inference about the wavelet variance using the estimators $\hat{u}_X(\tau_j)$ and $\hat{v}_X(\tau_j)$. We defer proofs to the Appendix, but we note that they are based on calculating mixed cumulants and require a technique sometimes called a diagram method. This method has been used widely to prove various central and non-central limit theorems involving functionals of Gaussian random variables; see e.g., Breuer and Major (1983), Giraitis and Surgailis (1985), Giraitis and Taqqu (1998), Fox and Taqqu (1987), Ho and Sun (1987) and the references therein. While building upon previous works, the proofs involve some unique and significantly different arguments that can be used to strengthen asymptotic results in other contexts, e.g., wavelet covariance estimation.

Theorem 5 Suppose X_t is a stationary Gaussian process whose SDF is square integrable, and suppose δ_t is a strictly stationary binary process (independent of X_t) such that Assumption 3 holds. Then $\hat{u}_X(\tau_j)$ is asymptotically normal with mean $\nu_X^2(\tau_j)$ and large sample variance $S_{u,j}(0)/M_j$, where $S_{u,j}$ is the SDF for $Z_{u,j,t}$.

Remark 6 *The Gaussian assumption on X_t can be dropped if we add appropriate mixing conditions, an approach that has been taken in the gap-free case (Serroukh et al., 2000). Since our estimators are essentially averages of stationary processes (10) and (11), asymptotic normality for the estimators (8) and (9) will follow if both X_t and the gap process δ_t possess appropriate mixing conditions. Moreover, construction of confidence intervals for the wavelet variance when X_t is non-Gaussian and the asymptotic normality of the estimators holds is same as what is described below. This incorporates robustness into the methods developed in this paper.*

Given a consistent estimator of $S_{u,j}(0)$, the above theorem can be used to construct an asymptotically correct confidence interval for $\nu_X^2(\tau_j)$. We use a multitaper spectral approach (Serroukh et al., 2000). Let

$$\tilde{Z}_{u,j,t} \equiv \sum_{l=0}^{L_j-1} \sum_{l'=0}^{L_j-1} h_{j,l} h_{j,l'} \hat{\beta}_{l,l'} X_{t-l} X_{t-l'} \delta_{t-l} \delta_{t-l'}, \quad t = L_j - 1, \dots, N - 1.$$

Let $\lambda_{k,t}$, $t = 0, \dots, M_j - 1$, for $k = 0, \dots, K - 1$ be the first K orthonormal Slepian tapers, where K is an odd integer. Define

$$J_{u,j,k} = \sum_{t=0}^{M_j-1} \lambda_{k,t} \tilde{Z}_{u,j,t+L_j-1}, \quad \lambda_{k,+} = \sum_{t=0}^{M_j-1} \lambda_{k,t}$$

and

$$\tilde{u}_j = \frac{\sum_{k=0,2,\dots}^{K-1} J_{u,j,k} \lambda_{k,+}}{\sum_{k=0,2,\dots}^{K-1} \lambda_{k,+}^2}.$$

We estimate $S_{u,j}(0)$ by

$$\hat{S}_{u,j}(0) = \frac{1}{K} \sum_{k=0}^{K-1} (J_{u,j,k} - \tilde{u}_j \lambda_{k,+})^2.$$

Following the recommendation of Serroukh et al. (2000), we choose $K = 5$ and set the bandwidth parameter so that the Slepian tapers are band-limited to the interval $[-\frac{7}{2M_j}, \frac{7}{2M_j}]$.

Previous Monte Carlo studies show that $\hat{S}_{u,j}(0)$ performs well (Serroukh et al., 2000).

We now turn to the large sample properties of the second estimator $\hat{\nu}_X(\tau_j)$, which closely resemble those for $\hat{\nu}_X(\tau_j)$.

Theorem 7 *Suppose X_t or its increments is a stationary Gaussian process whose SDF is such that $\sin^2(\pi f) S_X(f)$ is square integrable. Assume the same conditions on δ_t as in Theorem 5. Then $\hat{\nu}_X(\tau_j)$ is asymptotically normal with mean $\nu_X^2(\tau_j)$ and large sample variance $S_{v,j}(0)/M_j$, where $S_{v,j}$ is the SDF for $Z_{v,j,t}$.*

Based upon

$$\tilde{Z}_{v,j,t} \equiv -\frac{1}{2} \sum_{l=0}^{L_j-1} \sum_{l'=0}^{L_j-1} h_{j,l} h_{j,l'} \hat{\beta}_{l,l'} (X_{t-l} - X_{t-l'})^2 \delta_{t-l} \delta_{t-l'},$$

we can estimate $S_{v,j}(0)$ using the same multitaper approach as before.




Figure 1: Plot of asymptotic efficiency of $\hat{u}_X(\tau_3)$ with respect to $\hat{v}_X(\tau_3)$ under autoregressive (left) and fractionally differenced (right) models.

4.1 Efficiency study

The estimators $\hat{u}_X(\tau_j)$ and $\hat{v}_X(\tau_j)$ both work for stationary processes, whereas the latter can also be used for nonstationary processes with stationary increments. If $\hat{v}_X(\tau_j)$ performed better than $\hat{u}_X(\tau_j)$ in the stationary case, then the latter would be an unattractive estimator because it is restricted to just stationary processes. To address this issue, consider the asymptotic relative efficiency of the two estimators, which is given by the ratio of $S_{v,j}(0)$ to $S_{u,j}(0)$. For selected cases, this ratio can be computed to sufficient accuracy using the relationships

$$S_{u,j}(0) = \sum_{k=-\infty}^{\infty} s_{u,j,k} \quad \text{and} \quad S_{v,j}(0) = \sum_{k=-\infty}^{\infty} s_{v,j,k},$$

where $s_{u,j,k}$ and $s_{v,j,k}$ are the ACVSs corresponding to SDFs $S_{u,j}$ and $S_{v,j}$. We consider two cases, in both of which we use a level $j = 3$ Haar wavelet filter and assume that δ_t is a sequence of independent and identically distributed Bernoulli random variables with $\Pr(\delta_t = 1) = 0.9$. In the first case, we let X_t to be a first order autoregressive (AR(1)) process with $s_{X,k} = \phi^{|k|}$. The left-hand plot of Figure 1 shows the asymptotic relative efficiency as a function of ϕ . Except for ϕ close to unity, $\hat{u}_X(\tau_j)$ outperforms $\hat{v}_X(\tau_j)$. When ϕ is close to unity, the differencing inherent in $\hat{v}_X(\tau_j)$ makes it a more stable estimator than $\hat{u}_X(\tau_j)$, which is intuitively reasonable because the AR(1) process starts to resemble a random walk. For the second case, let X_t to be a stationary fractionally differenced (FD) process with $s_{X,k}$ satisfying

$$s_{X,0} = \frac{\Gamma(1-2\alpha)}{\Gamma(1-\alpha)\Gamma(1-\alpha)} \quad \text{and} \quad s_{X,k} = s_{X,k-1} \frac{k+\alpha-1}{k-\alpha}$$

for $k = 1, 2, \dots$; see, e.g., Granger and Joyeux (1980) and Hosking (1981). Here $\alpha < \frac{1}{2}$ is the long memory parameter, with $\alpha = 0$ corresponding to white noise and α close to $\frac{1}{2}$ corresponding to a highly correlated process whose ACVS damps down to zero very slowly. The right-hand plot of Figure 1 shows the asymptotic relative efficiency as a function of α .




Figure 2: Plot of a typical simulated gappy AR(1) time series and wavelet variances at various scales.

As α approaches $\frac{1}{2}$, the variogram-based estimator $\hat{v}_X(\tau_j)$ outperforms $\hat{u}_X(\tau_j)$. These two cases tell us that $\hat{u}_X(\tau_j)$ is not uniformly better than $\hat{v}_X(\tau_j)$ for stationary processes and that, even for these processes, differencing can help stabilize the variance. Experimentation with other Daubechies filters leads us to the same conclusions.

5 Monte Carlo study

The purpose of this Monte Carlo study is to assess the adequacy of the normal approximation in Theorem 5 and 7 for simple situations. We also look at the performance of the estimates of $S_{u,j}(0)$ and $S_{v,j}(0)$.

5.1 Autoregressive process of order 1

In the first example, we simulate 1000 time series of length 1024 from an AR(1) process with $\phi = 0.9$. For each time series, we simulate δ_t independent and identically from a Bernoulli distribution with $\Pr(\delta_t = 1) = p = 0.9$. For each simulated gappy series, we estimate wavelet variances at scales indexed by $j = 1, \dots, 6$ using $\hat{u}_X(\tau_j)$ and $\hat{v}_X(\tau_j)$ with the Haar wavelet filter. We also estimate the variance of the wavelet variances by using the multitaper method described in Section 4 and also from the sample variance of the Monte Carlo estimates. We then compare estimated values with the corresponding large sample approximations. Table 1 summarizes this experiment. Let $\hat{u}_{X,r}(\tau_j)$ and $\hat{v}_{X,r}(\tau_j)$ be the wavelet variance estimates for the r th realization, and let $\hat{S}_{u,j,r}(0)$ and $\hat{S}_{v,j,r}(0)$ be the corresponding multitaper estimates of $S_{u,j}(0)$ and $S_{v,j}(0)$. We note from Table 1 that the sample means of $\hat{u}_{X,r}(\tau_j)$ and $\hat{v}_{X,r}(\tau_j)$ are in excellent agreement with the true wavelet variance $\nu_X^2(\tau_j)$. The sample standard deviations of $\hat{u}_{X,r}(\tau_j)$ and $\hat{v}_{X,r}(\tau_j)$ are also in good agreement with $M_j^{-\frac{1}{2}} S_{u,j}^{\frac{1}{2}}(0)$ and $M_j^{-\frac{1}{2}} S_{v,j}^{\frac{1}{2}}(0)$. In particular, the ratios of the standard deviation of the $\hat{u}_{X,r}(\tau_j)$'s to their large sample approximations are quite close to unity, ranging between 0.884 and 1.005. The corresponding ratios for $\hat{v}_{X,r}(\tau_j)$ range between 0.926 and 1.002. We also consider the perfor-

Table 1: Summary of Monte Carlo results for AR(1) process

	j					
	1	2	3	4	5	6
$\nu_X^2(\tau_j)$	0.0500	0.0689	0.1079	0.1585	0.1907	0.1710
mean of $\hat{u}_{X,r}(\tau_j)$	0.0502	0.0690	0.1084	0.1593	0.1911	0.1716
mean of $\hat{v}_{X,r}(\tau_j)$	0.0503	0.0692	0.1085	0.1592	0.1910	0.1715
$M_j^{-\frac{1}{2}} S_{u,j}^{\frac{1}{2}}(0)$	0.0087	0.0057	0.0104	0.0230	0.0347	0.0429
s.d. of $\hat{u}_{X,r}(\tau_j)$	0.0076	0.0055	0.0101	0.0204	0.0338	0.0431
mean of $M_j^{-\frac{1}{2}} \hat{S}_{u,j,r}^{\frac{1}{2}}(0)$	0.0071	0.0047	0.0086	0.0175	0.0288	0.0340
$M_j^{-\frac{1}{2}} S_{v,j}^{\frac{1}{2}}(0)$	0.0027	0.0047	0.0102	0.0207	0.0345	0.0428
s.d. of $\hat{v}_{X,r}(\tau_j)$	0.0025	0.0044	0.0099	0.0205	0.0337	0.0428
mean of $M_j^{-\frac{1}{2}} \hat{S}_{v,j,r}^{\frac{1}{2}}(0)$	0.0022	0.0039	0.0085	0.0173	0.0285	0.0339

mance of the multitaper estimates. In particular, we find the sample means of $M_j^{-\frac{1}{2}} \hat{S}_{u,j,r}^{\frac{1}{2}}(0)$ and $M_j^{-\frac{1}{2}} \hat{S}_{v,j,r}^{\frac{1}{2}}(0)$ to be close to their respective theoretical values, but with a slight downward bias. Figure 2 plots the realization of the time series for which the sum of squares of errors $\sum_j \{\hat{u}_{X,r}(\tau_j) - \nu_X^2(\tau_j)\}^2$ is closest to the average sum of squares of errors, namely, $1000^{-1} \sum_r \sum_j \{\hat{u}_{X,r}(\tau_j) - \nu_X^2(\tau_j)\}^2$. For this typical realization, we also plot the estimated and theoretical wavelet variances with corresponding 95% confidence intervals. The black (gray) solid line in Figure 2 gives the estimated (theoretical) confidence intervals based on $\hat{u}_X(\tau_j)$, with the dotted lines indicating corresponding intervals based upon $\hat{v}_X(\tau_j)$. We see reasonable agreement between the theoretical and estimated values.

5.2 Kolmogrov turbulence

In the second example, we generate 1000 time series of length 1024 from an FD($\frac{5}{6}$) process, which is a nonstationary process that has properties very similar to Kolmogorov turbulence and hence is of interest in atmospheric science and oceanography. For each time series, we simulate the gaps δ_t as before. In this example increments of X_t rather X_t itself are stationary. Therefore we employ only $\hat{v}_X(\tau_j)$ and consider how well its variance is approximated by the large sample result stated in Theorem 7. Table 2 summarizes the results of this experiment using the Haar wavelet filter. Again we find that, for each level j , the average $\hat{v}_{X,r}(\tau_j)$ is in excellent agreement with the true $\nu_X^2(\tau_j)$; the sample standard deviation of $\hat{v}_{X,r}(\tau_j)$ is in good agreement with its large sample approximation; and the sample mean of $M_j^{-\frac{1}{2}} \hat{S}_{v,j}^{\frac{1}{2}}(0)$ is close to $M_j^{-\frac{1}{2}} S_{v,j}^{\frac{1}{2}}(0)$, with a slight downward bias. Figure 3 has the same format as Figure 2




Figure 3: Plot of a typical simulated gappy $FD(\frac{5}{6})$ time series and wavelet variances at various scales. Solid lines indicate the estimated intervals while dotted lines indicate the true intervals.

Table 2: Summary of Monte Carlo results for $FD(\frac{5}{6})$ process

	j					
	1	2	3	4	5	6
$\nu_X^2(\tau_j)$	0.2594	0.3078	0.4427	0.6831	1.0762	1.7050
mean of $\hat{\nu}_{X,r}(\tau_j)$	0.2599	0.3081	0.4421	0.6832	1.0771	1.7179
$M_j^{-\frac{1}{2}} S_{v,j}^{\frac{1}{2}}(0)$	0.0141	0.0203	0.0399	0.0857	0.1899	0.4281
s.d. of $\hat{\nu}_{X,r}(\tau_j)$	0.0129	0.0186	0.0386	0.0847	0.1877	0.4275
mean of $M_j^{-\frac{1}{2}} \hat{S}_{v,j,r}^{\frac{1}{2}}(0)$	0.0119	0.0168	0.0330	0.0704	0.1567	0.3489

and again indicates reasonable agreement between theoretical and estimated values.

6 Generalization of basic theory

6.1 Non-Daubechies wavelet filters

Although we formulated Theorems 5 and 7 in terms of the Daubechies wavelet filters, in fact they are valid for a wider class of filters. In particular, both theorems continue to hold for any filter $h_{j,l}$ that has finite width and sums to zero (if the original process X_t has mean zero, Theorem 5 only requires $h_{j,l}$ to be of finite width). This provides us with an estimation theory for wavelet variances other than those defined by a Daubechies wavelet filter. For example, at the unit scale, we can entertain the filter $\{-\frac{1}{4}, \frac{1}{2}, -\frac{1}{4}\}$, which can be considered

to be a discrete approximation of the Mexican hat wavelet.

6.2 Gappy d th order stationary increment process

Here we extend the basic theory to estimate the wavelet variance for a process X_t , $t \in \mathcal{Z}$, with d th order stationary increments Y_t . Let μ_Y be the mean, $s_{Y,k}$ the ACVS and $\gamma_{Y,k}$ the semi-variogram of Y_t . For $L \geq 2d$, an expression for the Daubechies wavelet variance that is analogous to (6) is

$$\nu_X^2(\tau_j) = \sum_{l=0}^{L_j-d-1} \sum_{l'=0}^{L_j-d-1} b_{j,l,d} b_{j,l',d} s_{Y,l-l'}, \quad (13)$$

where $b_{j,l,r}$ is the r th order cumulative summation of the Daubechies wavelet filter $h_{j,l}$, i.e.,

$$b_{j,l,0} = h_{j,l}, \quad b_{j,l,k} = \sum_{r=0}^l b_{j,r,k-1},$$

for $l = 0, \dots, L_j - k - 1$ (see Craigmile and Percival, 2005). Moreover, if $L > 2d$, we obtain the alternative expression

$$\nu_X^2(\tau_j) = - \sum_{l=0}^{L_j-d-1} \sum_{l'=0}^{L_j-d-1} b_{j,l,d} b_{j,l',d} \gamma_{Y,l-l'}. \quad (14)$$

We can now proceed to estimate $\nu_X^2(\tau_j)$ as follows. First we carry out d th order differencing of the observed X_t to obtain an observed Y_t . This will generate a new gap pattern that has more gaps than the old gap structure, but the new gap pattern will still be stationary and independent of Y_t . We then mimic the stationary ($d = 0$) case described as in Section 3 with $b_{j,l,d}$ replacing $h_{j,l}$, the new gap pattern replacing δ_t , and Y_t replacing X_t in the estimators (8) and (9). As a simple illustration of this scheme, consider the case $d = 2$. For $t = 2, 3, \dots$, compute $Y_t = X_t - 2X_{t-1} + X_{t-2}$ whenever $\delta_t = \delta_{t-1} = \delta_{t-2} = 1$. Let $\eta_t = 1$ if $\delta_t = \delta_{t-1} = \delta_{t-2} = 1$ and $= 0$ otherwise. Let

$$\hat{\rho}_{l,l'}^{-1} = \frac{1}{M_j} \sum_{t=L_j-3}^{N-1} \eta_{t-l} \eta_{t-l'},$$

where now M_j is redefined to be $N - L_j + 3$. Again $\hat{\rho}_{l,l'}^{-1}$ is a consistent estimator of $\rho_{l,l'}^{-1} = \Pr(\eta_{t-l} = 1, \eta_{t-l'} = 1)$. As before, assume $\hat{\rho}_{l,l'}^{-1} > 0$ for $l, l' = 0, \dots, L_j - 3$. The new versions of the estimators of $\nu_X^2(\tau_j)$ are then given by

$$\hat{u}_X(\tau_j) = \frac{1}{M_j} \sum_{t=L_j-3}^{N-1} \sum_{l=0}^{L_j-3} \sum_{l'=0}^{L_j-3} b_{j,l,2} b_{j,l',2} \hat{\rho}_{l,l'}^{-1} Y_{t-l} Y_{t-l'} \eta_{t-l} \eta_{t-l'},$$

and

$$\hat{v}_X(\tau_j) = - \frac{1}{2M_j} \sum_{t=L_j-3}^{N-1} \sum_{l'=0}^{L_j-3} \sum_{l=0}^{L_j-3} b_{j,l,2} b_{j,l',2} \hat{\rho}_{l,l'}^{-1} (Y_{t-l} - Y_{t-l'})^2 \eta_{t-l} \eta_{t-l'}.$$

The large sample properties of these estimators are given by obvious analogs to Theorems 5 and 7.

Theorem 8 Suppose X_t is a process whose d th order increments Y_t are a stationary Gaussian process with square integrable SDF, and suppose δ_t is a strictly stationary binary process (independent of X_t) such that the derived binary process η_t satisfies Assumption 3. Then, if $L \geq 2d$, $\hat{u}_X(\tau_j)$ is asymptotically normal with mean $\nu_X^2(\tau_j)$ and large sample variance $S_{d,u,j}(0)/M_j$. where $S_{d,u,j}$ is the SDF for $\sum_l \sum_{l'} b_{j,l,d} b_{j,l',d} \rho_{l,l'} Y_{t-l} Y_{t-l'} \eta_{t-l} \eta_{t-l'}$.

Theorem 9 Suppose X_t is a process whose increments of order $d + 1$ are a stationary Gaussian process with square integrable SDF, and suppose δ_t is as in the previous theorem. Then, if $L > 2d$, $\hat{v}_X(\tau_j)$ is asymptotically normal with mean $\nu_X^2(\tau_j)$ and large sample variance $S_{d,v,j}(0)/M_j$. where $S_{d,v,j}$ is the SDF for $-\frac{1}{2} \sum_l \sum_{l'} b_{j,l,d} b_{j,l',d} \rho_{l,l'} (Y_{t-l} - Y_{t-l'})^2 \eta_{t-l} \eta_{t-l'}$.

The proofs of Theorems 8 and 9 are similar to those of, respectively, Theorems 5 and 7 and thus are omitted.

Remark 10 Since each extra differencing produces more gaps, an estimate that requires less differencing will be more efficient. This is where the semi-variogram estimator $\hat{v}_X(\tau_j)$ comes in handy. Let C_t denote the backward differences of order $d-1$ X_t . Then C_t is not stationary but its increments are. Let the semi-variogram of C_t be denoted by $\gamma_{C,k}$. Then by virtue of (14), we can write for $L \geq 2d$

$$\nu_X^2(\tau_j) = - \sum_{l=0}^{L_j-d} \sum_{l'=0}^{L_j-d} b_{j,l,d-1} b_{j,l',d-1} \gamma_{C,l-l'}. \quad (15)$$

Thus alternatively we can proceed as follows. We carry out $d-1$ successive differences of X_t to obtain C_t and then use the semi-variogram estimator with the new gap structure and with the Daubechies filter replaced by $b_{j,l,d-1}$. Unlike the stationary case, this estimator often outperforms the covariance-type estimator that requires one more order of differencing.

6.3 Systematic gaps

We have focused on geophysical applications which tend to have gaps that are stochastic in nature. When systematic gaps occur, e.g., in financial time series when no trading takes place on weekends, we note that our estimates (8) and (9) produce valid unbiased estimate of the true wavelet variance as long as $\hat{\beta}_{l,l'}^{-1} > 0$ for $l, l' = 0, \dots, L_j - 1$ (for the financial example, this condition on $\hat{\beta}$ holds when the length of the time series N is sufficiently large); moreover, our large sample theory can be readily adjusted to handle those gaps. First, we redefine the theoretical β by taking the deterministic limit of $\hat{\beta}$ as N tends to infinity. Next we observe that the processes $Z_{u,j,t}$ and $Z_{v,j,t}$ defined via (10) and (11) are no longer stationary under this systematic gap pattern. To see this consider $j = 2$ and the Haar wavelet filter for which $L_2 = 4$. Then $Z_{u,2,t}$ for a Friday depends on the observations obtained from Tuesday to Friday while $Z_{u,2,t}$ for a Monday depends only on values of the time series observed on Monday and the previous Friday. As a consequence we can not invoke Theorem 5 or 7 directly. However, because the gaps have a period of a week, we can retrieve stationarity by summing $Z_{u,j,t}$ and $Z_{v,j,t}$ over 7 days; i.e., $\sum_{m=0}^6 Z_{u,j,t+m}$ and $\sum_{m=0}^6 Z_{v,j,t+m}$ are stationary processes. For large M_j the summations of t in estimators (8) and (9) are essentially sums




Figure 4: Atmospheric pressure data (left) from NOAA’s TAO buoy array and Haar wavelet variance estimates (right) for scales indexed by $j = 1, \dots, 8$.

over these stationary processes, plus terms that are asymptotically negligible. Thus we can prove asymptotic normality of (8) and (9) from the respective asymptotic normality of the averages of $\sum_{m=0}^6 Z_{u,j,t+m}$ and $\sum_{m=0}^6 Z_{v,j,t+m}$. The proofs are similar to those for Theorems 5 and 7, with some simplification because the gaps are deterministic (an alternative approach is to use Theorem 1 of Ho and Sun, 1987). Large sample confidence intervals can be constructed using the multitaper procedure described in Section 4.

7 Examples

7.1 Analysis of TAO data

We apply our techniques to daily atmospheric pressure data (Figure 4) collected over a period of 578 days by the Tropical Atmospheric Ocean (TAO) buoy array operated by the National Oceanic and Atmospheric Administration. There were 527 days of observed values and 51 days during which no observations were made. Shorter gaps in this time series are mainly due to satellite transmission problems. Equipment malfunctions that require buoy repairs result in longer gaps. It is reasonable to assume that the gaps are independent of the pressure values and are a realization of a stationary process. Of particular interest are contributions to the overall variability due to different dynamical phenomena, including an annual cycle, interseasonal oscillations and a menagerie of tropical waves and disturbances associated with small time scales. We employ wavelet variance estimators (8) and (9) using the Haar wavelet filter.

Estimated wavelet variances for levels $j = 1, \dots, 8$ are plotted in Figure 4 along with the 95% confidence intervals (solid and dotted lines for, respectively, $\hat{u}_X(\tau_j)$ and $\hat{v}_X(\tau_j)$). We see close agreement between these two estimation procedures. Note that the wavelet variance is largest at scales τ_7 and τ_8 , which correspond to periods of, respectively, 128–256 days and 256–512 days. Large variability at these scales is due to a strong yearly cycle in the data. Apart from this, we also see a much weaker peak at scale τ_5 , which corresponds to a period

of 32–64 days and captures the interseasonal variability. Note also that there is hardly any variability at scale τ_1 , although there is some at scales τ_2 , τ_3 and τ_4 , indicating relatively important contributions to the variance due to disturbances at all but the very smallest scale. (We obtained similar results using the Daubechies $L = 4$ extremal phase and $L = 8$ least asymmetric wavelet filters.)

7.2 Nile River minima

This time series (Figure 5) consists of measurements of minimum yearly water level of the Nile River over the years 622–1921, with 622–1284 representing the longest segment without gaps (Toussoun, 1925). The rate of gaps is about 43% after year 1285. Several authors have previously analyzed the initial gap free segment (see, e.g., Beran, 1994, and Percival and Walden, 2000). The entire series, including the gappy part, has been analyzed based on a parametric state space model (Palma and Del Pino, 1999), in contrast to our nonparametric approach. Historical records indicate a change around 715 in the way the series was measured. For the gap free segment, there is more variability at scales τ_1 and τ_2 before 715 than after (Whitcher et al., 2002). Therefore we restrict ourselves to the period 716–1921. Figure 5 plots wavelet variance estimates up to scale τ_8 along with 95% confidence intervals using $\hat{\nu}_X(\tau_j)$ with the Haar wavelet filter. Here solid lines stand for the gap free segment 716–1284, and dotted lines for the gappy segment 1286–1921. Except at scales τ_1 , τ_6 and τ_8 , we see reasonably good agreement between estimates from the two segments. Substantial uncertainties due to the large number of gaps are reflected in the larger confidence intervals for the gappy segment. Under the assumption that the statistical properties of the Nile River were the same throughout 716–1921, we could combine the two segments to produce overall estimates and confidence intervals for the wavelet variances; however, this assumption is questionable at certain scales. Over the years 1286–1470, there are only six gaps. Separate analysis of this segment suggests more variability at scales τ_1 and τ_2 than what was observed in 716–1284. In addition, construction of the first Aswan Dam starting in 1899 changed the nature of the Nile River in the subsequent years. However, a wavelet variance analysis over 1286–1898 (omitting the years after the dam was built) does not differ much from that of 1286–1921. Thus the apparent increase in variability at the largest scales from segment 716–1284 to 1286–1921 cannot be attributed just to the influence of the dam.

8 Discussion

In Section 3 we made the crucial assumption that, for a fixed j , $\hat{\beta}_{l,l'}^{-1} > 0$ when $l, l' = 0, \dots, L_j - 1$. For small sample sizes, this condition might fail to hold. This situation arises mainly when half or more of the observations are missing and can be due to systematic periodic patterns in the gaps. For example, if δ_t alternates between zero and one, then $\hat{\beta}_{0,1}^{-1}$ is zero, reflecting the fact that the observed time series does not contain relevant information about $\nu_X^2(\tau_1)$. A methodology different from what we have discussed might be able to handle some gap patterns for which $\hat{\beta}_{l,l'}^{-1} = 0$. In particular, generalized prolate spheroidal sequences have been used to handle spectral estimation of irregularly sampled processes (Bronez, 1988). This approach in essence corresponds to the construction of special filters and could be used to construct approximations to the Daubechies filters when $\hat{\beta}_{l,l'}^{-1} = 0$.




Figure 5: Nile River minima (left) and Haar wavelet variance estimates (right) for scales indexed by $j = 1, \dots, 8$.

Estimation of the SDF for gappy time series is a long-standing difficult problem. In Section 1 we noted that the wavelet variance provides a simple and useful estimator of the integral of the SDF over a certain octave band. In particular, the Blackman–Tukey pilot spectrum (Blackman and Tukey, 1958, Sec. 18) coincides with the Haar wavelet variance. Recently Tsakiroglou and Walden (2002) generalized this pilot spectrum by utilising the (maximal overlap) discrete wavelet packet transform. The result is an SDF estimator that is competitive with existing estimators. With a similar generalization, our wavelet variance estimator for gappy time series can be adapted to serve as an SDF estimator. Moreover, Nason et al. (2000) used shrinkage of squared wavelet coefficients to estimate spectra for locally stationary processes. In the same vein, we can apply wavelet shrinkage to the $Z_{u,j,t}$ or $Z_{v,j,t}$ processes to estimate time-varying spectra when the original time series is observed with gaps.

Finally we note a generalization of interest in the analysis of multivariate gappy time series. Given two time series $X_{1,t}$ and $X_{2,t}$, the wavelet cross covariance yields a scale-based analysis of the cross covariance between the two series in a manner similar to wavelet variance analysis (for estimation of the wavelet cross covariance, see Whitcher et al., 2000, and the references therein). The methodology described in this paper can be readily adapted to estimate the wavelet cross covariance for multivariate time series with gaps.

Proofs

We first need the followings propositions and lemmas. To avoid a triviality, we assume throughout that $\text{var}\{X_t\} > 0$.

Proposition 11 *Let $\{X_t\}$ be a real-valued zero mean Gaussian process with ACVS $s_{X,k}$ and with SDF S_X that is square integrable over $[-\frac{1}{2}, \frac{1}{2}]$. Then, for any choice of k, k', l and l' , the bivariate process $\mathbf{U}_t = [X_{t-k}X_{t-k'}, X_{t-l}X_{t-l'}]^T$ has a spectral matrix $\mathcal{S}_{\mathbf{U}}$ that is continuous.*

Proof of Proposition 11. Using the Isserlis (1918) theorem, we have

$$\text{cov} \left(X_{t-k} X_{t-k'}, X_{t-l+\tau} X_{t-l'+\tau} \right) = s_{X,k-l+\tau} s_{X,k'-l'+\tau} + s_{X,k-l'+\tau} s_{X,k'-l+\tau}.$$

Since

$$s_{X,\tau} = \int_{-1/2}^{1/2} S_X(f) e^{i2\pi f\tau} df = \int_{-1/2}^{1/2} S_X(f) e^{-i2\pi f\tau} df,$$

it follows that

$$\begin{aligned} & \text{cov} \left(X_{t-k} X_{t-k'}, X_{t-l+\tau} X_{t-l'+\tau} \right) \\ &= \int_{-1/2}^{1/2} \int_{-1/2}^{1/2} e^{i2\pi f'(k-l+\tau) - i2\pi f''(k'-l'+\tau)} S_X(f') S_X(f'') df' df'' \\ &+ \int_{-1/2}^{1/2} \int_{-1/2}^{1/2} e^{i2\pi f'(k-l'+\tau) - i2\pi f''(k'-l+\tau)} S_X(f') S_X(f'') df' df''. \end{aligned}$$

Interchanging the order of the integrations and letting $f = f' - f''$ so that $f'' = f' - f$, we have

$$\begin{aligned} & \text{cov} \left(X_{t-k} X_{t-k'}, X_{t-l+\tau} X_{t-l'+\tau} \right) \\ &= \int_{-1/2}^{1/2} \int_{-1/2}^{1/2} e^{i2\pi f'(k-l+\tau) - i2\pi f''(k'-l'+\tau)} S_X(f') S_X(f'') df'' df' \\ &+ \int_{-1/2}^{1/2} \int_{-1/2}^{1/2} e^{i2\pi f'(k-l'+\tau) - i2\pi f''(k'-l+\tau)} S_X(f') S_X(f'') df'' df' \\ &= - \int_{-1/2}^{1/2} \int_{f'+\frac{1}{2}}^{f'-\frac{1}{2}} e^{i2\pi \{ f'(k-l+\tau) + (f-f')(k'-l'+\tau) \}} S_X(f') S_X(f-f') df df' \\ &- \int_{-1/2}^{1/2} \int_{f'+\frac{1}{2}}^{f'-\frac{1}{2}} e^{i2\pi \{ f'(k-l'+\tau) + (f-f')(k'-l+\tau) \}} S_X(f') S_X(f-f') df df' \\ &= \int_{-1/2}^{1/2} \int_{f'-\frac{1}{2}}^{f'+\frac{1}{2}} e^{i2\pi \{ f'(k-l+\tau) + (f-f')(k'-l'+\tau) \}} S_X(f') S_X(f-f') df df' \\ &+ \int_{-1/2}^{1/2} \int_{f'-\frac{1}{2}}^{f'+\frac{1}{2}} e^{i2\pi \{ f'(k-l'+\tau) + (f-f')(k'-l+\tau) \}} S_X(f') S_X(f-f') df df'. \end{aligned}$$

Because the inner integrands in each of the above double integrals is a periodic function of f with a period of unity, we have

$$\begin{aligned} & \text{cov} \left(X_{t-k} X_{t-k'}, X_{t-l+h} X_{t-l'+h} \right) \\ &= \int_{-1/2}^{1/2} \int_{-1/2}^{1/2} e^{i2\pi [f'(k-l+\tau) + (f-f')(k'-l'+\tau)]} S_X(f') S_X(f-f') df' df \\ &+ \int_{-1/2}^{1/2} \int_{-1/2}^{1/2} e^{i2\pi [f'(k-l'+\tau) + (f-f')(k'-l+\tau)]} S_X(f') S_X(f-f') df' df \end{aligned}$$

$$= \int_{-1/2}^{1/2} e^{i2\pi f\tau} S_{k,k',l,l'}(f) df,$$

where the cross-spectrum between $\{X_{t-k}X_{t-k'}\}$ and $\{X_{t-l}X_{t-l'}\}$ is given by

$$\begin{aligned} & S_{k,k',l,l'}(f) \\ &= \int_{-1/2}^{1/2} \left(e^{i2\pi [f'(k-l-k'+l')+f(k'-l')]} + e^{i2\pi [f'(k-l'-k'+l)+f(k'-l)]} \right) S_X(f') S_X(f-f') df' \\ &= e^{i2\pi f(k'-l')} \int_{-1/2}^{1/2} e^{i2\pi f'(k-l-k'+l')} S_X(f') S_X(f-f') df' \\ &\quad + e^{i2\pi f(k'-l)} \int_{-1/2}^{1/2} e^{i2\pi f'(k+l-k'-l')} S_X(f') S_X(f-f') df'. \end{aligned}$$

Because $e^{i2\pi f(k'-l')}$ is a continuous function of f , we can establish the continuity of the first term above if we can show that

$$A_{k,k',l,l'}(f) = \int_{-1/2}^{1/2} e^{i2\pi f'(k-l-k'+l')} S_X(f') S_X(f-f') df'$$

is a continuous function, from which the continuity of the second term – and hence of $S_{k,k',l,l'}$ itself – follows immediately. Recalling that $|e^{ix}| = 1$ for all x , the Cauchy–Schwarz inequality says that

$$\begin{aligned} & |A_{k,k',l,l'}(f+\rho) - A_{k,k',l,l'}(f)| \\ &= \left| \int_{-1/2}^{1/2} e^{i2\pi f'(k-l-k'+l')} S_X(f') [S_X(f+\rho-f') - S_X(f-f')] df' \right| \\ &\leq \left(\int_{-1/2}^{1/2} S_X^2(f') df' \int_{-1/2}^{1/2} |S_X(f+\rho-f') - S_X(f-f')|^2 df' \right)^{1/2} \end{aligned}$$

By hypothesis $\int_{-1/2}^{1/2} S_X^2(f') df'$ is finite, while

$$\int_{-1/2}^{1/2} |S_X(f+\rho-f') - S_X(f-f')|^2 df' \rightarrow 0 \text{ as } \rho \rightarrow 0$$

by Lemma 1.11, p. 37, Zygmund (1978). Hence $A_{k,k',l,l'}$ and $S_{k,k',l,l'}$ are continuous. Since

$$\mathcal{S}_U(f) = \begin{bmatrix} S_{k,k',k,k'}(f) & S_{k,k',l,l'}(f) \\ S_{l,l',k,k'}(f) & S_{l,l',l,l'}(f) \end{bmatrix},$$

we have established the continuity of the spectral matrix. ■

Proposition 12 *Let $h_{j,l}$ be any filter of width L_j . As in Proposition 11, let*

$$\begin{aligned} & S_{k,k',l,l'}(f) \\ &= \int_{-1/2}^{1/2} \left(e^{i2\pi[f'(k-l-k'+l')+f(k'-l')]} + e^{i2\pi[f'(k-l'-k'+l)+f(k'-l)]} \right) S_X(f') S_X(f-f') \, df', \end{aligned}$$

where we assume S_X to be square integrable. Then we must have

$$\sum_{k,k'} \sum_{l,l'} h_{j,k} h_{j,k'} h_{j,l} h_{j,l'} S_{k,k',l,l'}(0) > 0.$$

Proof of Proposition 12. We know that

$$H_j(f) = \sum_{l=0}^{L_j-1} h_{j,l} e^{-i2\pi fl}$$

is the Fourier transform of $h_{j,l}$. Using the definition of $S_{k,k',l,l'}(f)$, we have

$$\begin{aligned} & \sum_{k,k'} \sum_{l,l'} h_{j,k} h_{j,k'} h_{j,l} h_{j,l'} S_{k,k',l,l'}(0) \\ &= \int_{-1/2}^{1/2} \sum_{k,k'} \sum_{l,l'} h_{j,k} h_{j,k'} h_{j,l} h_{j,l'} \left(e^{i2\pi f(k-l-k'+l')} + e^{i2\pi f(k-l'-k'+l)} \right) S_X^2(f) \, df \\ &= \int_{-1/2}^{1/2} \left(\sum_k h_{j,k} e^{i2\pi fk} \sum_{k'} h_{j,k'} e^{-i2\pi fk'} \sum_l h_{j,l} e^{-i2\pi fl} \sum_{l'} h_{j,l'} e^{i2\pi fl'} \right. \\ &\quad \left. + \sum_k h_{j,k} e^{i2\pi fk} \sum_{k'} h_{j,k'} e^{-i2\pi fk'} \sum_l h_{j,l} e^{i2\pi fl} \sum_{l'} h_{j,l'} e^{-i2\pi fl'} \right) S_X^2(f) \, df \\ &= \int_{-1/2}^{1/2} \left\{ H_j^2(-f) H_j^2(f) + H_j^2(-f) H_j^2(f) \right\} S_X^2(f) \, df \\ &= 2 \int_{-1/2}^{1/2} \mathcal{H}_j^2(f) S_X^2(f) \, df. \end{aligned}$$

The above integral must be nonnegative. We claim that it is strictly positive. If not, then

$$\int_{-1/2}^{1/2} \mathcal{H}_j^2(f) S_X^2(f) \, df = 0.$$

A standard result in measure theory says that, if h is nonnegative on $[-\frac{1}{2}, \frac{1}{2}]$, then $h(f) = 0$ almost everywhere if and only if $\int_{-1/2}^{1/2} h(f) \, df = 0$; see, e.g., Corollary 4.10, p. 34, Bartle (1966). From the fundamental theorem of algebra, \mathcal{H}_j can only be zero at a finite number of frequencies. Since $\text{var} \{X_t\} > 0$, S_X can not be zero almost everywhere. Hence the integrand can not be zero almost everywhere, leading to a contradiction and thus establishing the proposition. \blacksquare

Proposition 13 Let $\{X_t\}$ be a real-valued zero mean Gaussian process with ACVS $s_{X,k}$ and SDF S_X satisfying

$$\int_{-1/2}^{1/2} \sin^4(2\pi f) S_X^2(f) df < \infty.$$

Then the bivariate process $\mathbf{U}_t = [\frac{1}{2}(X_{t-k} - X_{t-k'})^2, \frac{1}{2}(X_{t-l} - X_{t-l'})^2]^T$, for any choice of k, k', l and l' , has a spectral matrix $\mathcal{S}_{\mathbf{U}}$ that is continuous.

Proof of Proposition 13. By the Isserlis (1918) theorem,

$$\begin{aligned} & \text{cov} \left\{ (X_{t-k} - X_{t-k'})^2, (X_{t-l+m} - X_{t-l'+m})^2 \right\} \\ &= \text{cov} \left\{ X_{t-k}^2 - 2X_{t-k}X_{t-k'} + X_{t-k'}^2, X_{t-l+m}^2 - 2X_{t-l+m}X_{t-l'+m} + X_{t-l'+m}^2 \right\} \\ &= \text{cov}(X_{t-k}^2, X_{t-l+m}^2) - 2\text{cov}(X_{t-k}^2, X_{t-l+m}X_{t-l'+m}) + \text{cov}(X_{t-k}^2, X_{t-l'+m}^2) \\ &\quad - 2\text{cov}(X_{t-k}X_{t-k'}, X_{t-l+m}^2) \\ &\quad + 4\text{cov}(X_{t-k}X_{t-k'}, X_{t-l+m}X_{t-l'+m}) - 2\text{cov}(X_{t-k}X_{t-k'}, X_{t-l'+m}^2) \\ &\quad + \text{cov}(X_{t-k'}^2, X_{t-l+m}^2) - 2\text{cov}(X_{t-k'}^2, X_{t-l+m}X_{t-l'+m}) + \text{cov}(X_{t-k'}^2, X_{t-l'+m}^2) \\ &= 2s_{m+k-l}^2 - 4s_{m+k-l}s_{m+k-l'} + 2s_{m+k-l'}^2 + 2s_{m+k'-l}^2 - 4s_{m+k-l}s_{m+k'-l'} + 2s_{m+k'-l'}^2 \\ &\quad - 4s_{m+k-l}s_{m+k'-l} + 4s_{m+k-l}s_{m+k'-l'} + 4s_{m+k'-l}s_{m+k-l'} - 4s_{m+k-l'}s_{m+k'-l'} \\ &= 2(s_{m+k-l} - s_{m+k'-l} - s_{m+k-l'} + s_{m+k'-l'})^2. \end{aligned}$$

Since

$$s_{X,m} = \int_{-1/2}^{1/2} S_X(f) e^{i2\pi f m} df = \int_{-1/2}^{1/2} S_X(f) e^{-i2\pi f m} df,$$

it follows that

$$\begin{aligned} & \text{cov} \left\{ (X_{t-k} - X_{t-k'})^2, (X_{t-l+m} - X_{t-l'+m})^2 \right\} \\ &= 2 \left[\int_{-1/2}^{1/2} e^{i2\pi f' m} S_X(f') \left(e^{i2\pi f' k} - e^{i2\pi f' k'} \right) \left(e^{-i2\pi f' l} - e^{-i2\pi f' l'} \right) df' \right]^2 \\ &= 2 \left[\int_{-1/2}^{1/2} e^{i2\pi f' m} S_X(f') e^{-i2\pi f' (k-l)} \left(1 - e^{-i2\pi f' (k-k')} \right) \left(1 - e^{-i2\pi f' (l-l')} \right) df' \right]^2. \end{aligned}$$

Without loss of generality, assume $k \geq k'$ and $l \geq l'$. Then we can write

$$1 - e^{-i2\pi f' (k-k'-1)} = (1 - e^{-i2\pi f'}) \sum_{r=0}^{k-k'} e^{-i2\pi f' r}$$

and

$$1 - e^{i2\pi f' (l-l'-1)} = (1 - e^{i2\pi f'}) \sum_{r'=0}^{l-l'} e^{i2\pi f' r'}.$$

Thus

$$\begin{aligned} & \text{cov} \left\{ (X_{t-k} - X_{t-k'})^2, (X_{t-l+m} - X_{t-l'+m})^2 \right\} \\ &= 2 \int_{-1/2}^{1/2} \int_{-1/2}^{1/2} \left(e^{i2\pi(f'-f'')(k-l+m)} |1 - e^{i2\pi f'}|^2 |1 - e^{-i2\pi f''}|^2 S_X(f') S_X(-f'') \right) \\ & \quad \times \left(\sum_{r=0}^{k-k'-1} e^{-i2\pi f' r} \sum_{r=0}^{k-k'-1} e^{i2\pi f'' r} \sum_{r'=0}^{l-l'-1} e^{i2\pi f' r'} \sum_{r'=0}^{l-l'-1} e^{-i2\pi f'' r'} \right) df' df''. \end{aligned}$$

Interchanging the order of the integrations and letting $f = f' - f''$ so that $f'' = f' - f$, we have

$$\begin{aligned} & \text{cov} \left\{ (X_{t-k} - X_{t-k'})^2, (X_{t-l+m} - X_{t-l'+m})^2 \right\} \\ &= 2 \int_{-1/2}^{1/2} e^{i2\pi f m} \int_{-1/2}^{1/2} e^{i2\pi f(k-l)} \left([2 \sin(\pi f')]^2 S_X(f') [2 \sin \pi(f-f')]^2 S_X(f-f') \right) \\ & \quad \times \left(\sum_{r=0}^{k-k'-1} e^{-i2\pi f' r} \sum_{r=0}^{k-k'-1} e^{-i2\pi(f-f')r} \sum_{r'=0}^{l-l'-1} e^{i2\pi f' r'} \sum_{r'=0}^{l-l'-1} e^{-i2\pi(f-f')r'} \right) df' df \end{aligned}$$

Hence the cross-spectrum between $\{\frac{1}{2}(X_{t-k} - X_{t-k'})^2\}$ and $\{\frac{1}{2}(X_{t-l} - X_{t-l'})^2\}$ is given by

$$\begin{aligned} & S_{k,k',l,l'}(f) \\ &= \frac{1}{2} \int_{-1/2}^{1/2} e^{i2\pi f(k-l)} D(f') D(f-f') [2 \sin \pi f']^2 S_X(f') [2 \sin \pi(f-f')]^2 S_X(f-f') df', \end{aligned}$$

where

$$D(f) = \sum_{r=0}^{k-k'-1} \sum_{r'=0}^{l-l'-1} e^{-i2\pi f' r} e^{i2\pi f' r'}.$$

Because $[2 \sin(\pi f)]^2 S_X(f)$ defines a square integrable function, each individual term in the summation form of $S_{k,k',l,l'}(f)$ is a continuous function of f (see the argument given in Proposition 11). Hence $S_{k,k',l,l'}(f)$ is a continuous function of f . Since k, k', l and l' are arbitrary, it follows that the spectral matrix \mathbf{S}_U is continuous. \blacksquare

Proposition 14 *Assume the conditions of Proposition 13, and let $S_{k,k',l,l'}(f)$ be as defined in that proposition. Then*

$$\sum_{k,k'} \sum_{l,l'} h_{j,k} h_{j,k'} h_{j,l} h_{j,l'} S_{k,k',l,l'}(0) > 0.$$

Proof of Proposition 14. As before, we have

$$H_j(f) = \sum_{l=0}^{L_j-1} h_{j,l} e^{-i2\pi f l}.$$

Using the definition of $S_{k,k',l,l'}(f)$, we have

$$\begin{aligned}
& \sum_{k,k'} \sum_{l,l'} h_{j,l} h_{j,l'} h_{j,k} h_{j,k'} S_{k,k',l,l'}(0) \\
&= \frac{1}{2} \int_{-1/2}^{1/2} \sum_{k,k'} \sum_{l,l'} h_{j,l} h_{j,l'} h_{j,k} h_{j,k'} \left(e^{i2\pi f k} - e^{i2\pi f k'} \right) \left(e^{-i2\pi f k} - e^{-i2\pi f k'} \right) \\
&\quad \left(e^{-i2\pi f l} - e^{-i2\pi f l'} \right) \left(e^{i2\pi f l} - e^{i2\pi f l'} \right) S_X^2(f) \, df \\
&= \frac{1}{2} \int_{-1/2}^{1/2} \left[\sum_k h_{j,k} \sum_{k'} h_{j,k'} \left(e^{i2\pi f k} - e^{i2\pi f k'} \right) \left(e^{-i2\pi f k} - e^{-i2\pi f k'} \right) \right] \\
&\quad \times \left[\sum_l h_{j,l} \sum_{l'} h_{j,l'} \left(e^{-i2\pi f l} - e^{-i2\pi f l'} \right) \left(e^{i2\pi f l} - e^{i2\pi f l'} \right) \right] S_X^2(f) \, df \\
&= 2 \int_{-1/2}^{1/2} \left(H_j(-f) H_j(0) - |H_j(f)|^2 \right) \left(H_j(f) H_j(0) - |H_j(f)|^2 \right) S_X^2(f) \, df \\
&= 2 \int_{-1/2}^{1/2} \mathcal{H}_j^2(f) S_X^2(f) \, df
\end{aligned}$$

where we have used the fact that $H_j(0) = \sum_l h_{j,l} = 0$. The remainder of the proof follows as in Proposition 12. \blacksquare

We need the following lemma which we use to derive the formulas for $S_{u,j}$ and $S_{v,j}$ and also use later to prove Theorem 5 and 7.

Lemma 15 *Let $\{U_{l,l',t}\}$ and $\{V_{l,l',t}\}$ be stationary processes that are independent of each other for any choice of k, k', l and l' . Let*

$$\begin{aligned}
U_{l,l',t} &= \psi_{l,l'} + \int_{-1/2}^{1/2} e^{i2\pi f t} d\mathcal{U}_{l,l'}(f) \\
V_{l,l',t} &= \omega_{l,l'} + \int_{-1/2}^{1/2} e^{i2\pi f t} d\mathcal{V}_{l,l'}(f)
\end{aligned}$$

be their respective spectral representations. For any k, k', l and l' , let $S_{k,k',l,l'}$ and $G_{k,k',l,l'}$ denote the respective cross spectrum between $\{U_{k,k',t}\}$ and $\{U_{l,l',t}\}$ and between $\{V_{k,k',t}\}$ and $\{V_{l,l',t}\}$. Let $a_{l,l'}$ be fixed real numbers. Define

$$Q_t = \sum_{l,l'} a_{l,l'} (U_{l,l',t} V_{l,l',t} - \psi_{l,l'} \omega_{l,l'}).$$

Then $\{Q_t\}$ is a second order stationary process whose spectral density function is given by

$$S_Q(f) = \sum_{k,k'} \sum_{l,l'} a_{k,k'} a_{l,l'} [\psi_{k,k'} \psi_{l,l'} G_{k,k',l,l'}(f) + \omega_{k,k'} \omega_{l,l'} S_{k,k',l,l'}(f) + S * G_{k,k',l,l'}(f)], \quad (16)$$

where

$$S * G_{k,k',l,l'}(f) = \int_{-1/2}^{1/2} G_{k,k',l,l'}(f - f') S_{k,k',l,l'}(f') \, df'.$$

Proof of Lemma 15. First note that, because of the independence assumption,

$$E\{Q_t\} = \sum_{l,l'} a_{l,l'} E\{U_{l,l',t}V_{l,l',t} - \psi_{l,l'}\omega_{l,l'}\} = 0$$

which is independent of t . Next note that

$$\text{cov}\{Q_t, Q_{t+m}\} = \sum_{k,k'} \sum_{l,l'} a_{k,k'} a_{l,l'} \text{cov}\{U_{k,k',t}V_{k,k',t}, U_{l,l',t+m}V_{l,l',t+m}\}.$$

Now

$$\begin{aligned} & \text{cov}\{U_{k,k',t}V_{k,k',t}, U_{l,l',t+m}V_{l,l',t+m}\} \\ &= \text{cov}\left\{\left(\psi_{k,k'} + \int_{-1/2}^{1/2} e^{i2\pi ft} d\mathcal{U}_{k,k'}(f)\right)\left(\omega_{k,k'} + \int_{-1/2}^{1/2} e^{i2\pi ft} d\mathcal{V}_{k,k'}(f)\right),\right. \\ & \quad \left.\left(\psi_{l,l'} + \int_{-1/2}^{1/2} e^{i2\pi f'(t+m)} d\mathcal{U}_{l,l'}(f')\right)\left(\omega_{l,l'} + \int_{-1/2}^{1/2} e^{i2\pi f'(t+m)} d\mathcal{V}_{l,l'}(f')\right)\right\} \\ &= E\left\{\left(\psi_{k,k'} + \int_{-1/2}^{1/2} e^{-i2\pi ft} d\mathcal{U}_{k,k'}^*(f)\right)\left(\omega_{k,k'} + \int_{-1/2}^{1/2} e^{-i2\pi ft} d\mathcal{V}_{k,k'}^*(f)\right)\right. \\ & \quad \times \left.\left(\psi_{l,l'} + \int_{-1/2}^{1/2} e^{i2\pi f'(t+m)} d\mathcal{U}_{l,l'}(f')\right)\left(\omega_{l,l'} + \int_{-1/2}^{1/2} e^{i2\pi f'(t+m)} d\mathcal{V}_{l,l'}(f')\right)\right\} \\ & \quad - \psi_{k,k'}\omega_{k,k'}\psi_{l,l'}\omega_{l,l'} \\ &= E\left\{\left(\psi_{k,k'} + \int_{-1/2}^{1/2} e^{-i2\pi ft} d\mathcal{U}_{k,k'}^*(f)\right)\left(\psi_{l,l'} + \int_{-1/2}^{1/2} e^{i2\pi f'(t+m)} d\mathcal{U}_{l,l'}(f')\right)\right\} \\ & \quad \times E\left\{\left(\omega_{k,k'} + \int_{-1/2}^{1/2} e^{-i2\pi ft} d\mathcal{V}_{k,k'}^*(f)\right)\left(\omega_{l,l'} + \int_{-1/2}^{1/2} e^{i2\pi f'(t+m)} d\mathcal{V}_{l,l'}(f')\right)\right\} \\ & \quad - \psi_{k,k'}\omega_{k,k'}\psi_{l,l'}\omega_{l,l'} \\ &= \left(\psi_{k,k'}\psi_{l,l'} + \int_{-1/2}^{1/2} e^{i2\pi fm} S_{k,k',l,l'}(f) df\right)\left(\omega_{k,k'}\omega_{l,l'} + \int_{-1/2}^{1/2} e^{i2\pi fm} G_{k,k',l,l'}(f) df\right) \\ & \quad - \psi_{k,k'}\omega_{k,k'}\psi_{l,l'}\omega_{l,l'} \\ &= \psi_{k,k'}\psi_{l,l'} \int_{-1/2}^{1/2} e^{i2\pi fm} G_{k,k',l,l'}(f) df + \omega_{k,k'}\omega_{l,l'} \int_{-1/2}^{1/2} e^{i2\pi fm} S_{k,k',l,l'}(f) df \\ & \quad + \int_{-1/2}^{1/2} e^{i2\pi fm} S_{k,k',l,l'}(f) df \int_{-1/2}^{1/2} e^{i2\pi fm} G_{k,k',l,l'}(f) df \\ &= \int_{-1/2}^{1/2} e^{i2\pi fm} [\psi_{k,k'}\psi_{l,l'} G_{k,k',l,l'}(f) + \omega_{k,k'}\omega_{l,l'} S_{k,k',l,l'}(f)] df \\ & \quad + \int_{-1/2}^{1/2} \int_{-1/2}^{1/2} e^{i2\pi(f+f')m} G_{k,k',l,l'}(f') df' S_{k,k',l,l'}(f) df. \end{aligned}$$

Now, letting $f'' = f + f'$, we have

$$\begin{aligned} & \int_{-1/2}^{1/2} e^{i2\pi(f+f')m} G_{k,k',l,l'}(f') \, df' \\ &= \int_{f-\frac{1}{2}}^{f+\frac{1}{2}} e^{i2\pi f''m} G_{k,k',l,l'}(f'' - f) \, df'' = \int_{-1/2}^{1/2} e^{i2\pi f''m} G_{k,k',l,l'}(f'' - f) \, df'' \end{aligned}$$

because the integrand is a periodic function with unit period. Hence

$$\begin{aligned} & \text{cov} \left\{ U_{k,k',t} V_{k,k',t}, U_{l,l',t+m} V_{l,l',t+m} \right\} \\ &= \int_{-1/2}^{1/2} e^{i2\pi fm} [\psi_{k,k'} \psi_{l,l'} G_{k,k',l,l'}(f) + \omega_{k,k'} \omega_{l,l'} S_{k,k',l,l'}(f)] \, df \\ &+ \int_{-1/2}^{1/2} \int_{-1/2}^{1/2} e^{i2\pi f''m} G_{k,k',l,l'}(f'' - f) \, df'' S_{k,k',l,l'}(f) \, df \\ &= \int_{-1/2}^{1/2} e^{i2\pi fm} [\psi_{k,k'} \psi_{l,l'} G_{k,k',l,l'}(f) + \omega_{k,k'} \omega_{l,l'} S_{k,k',l,l'}(f)] \, df \\ &+ \int_{-1/2}^{1/2} \int_{-1/2}^{1/2} e^{i2\pi f''m} G_{k,k',l,l'}(f'' - f) S_{k,k',l,l'}(f) \, df \, df'' \\ &= \int_{-1/2}^{1/2} e^{i2\pi fm} [\psi_{k,k'} \psi_{l,l'} G_{k,k',l,l'}(f) + \omega_{k,k'} \omega_{l,l'} S_{k,k',l,l'}(f)] \, df \\ &+ \int_{-1/2}^{1/2} \int_{-1/2}^{1/2} e^{i2\pi fm} G_{k,k',l,l'}(f - f') S_{k,k',l,l'}(f') \, df' \, df \\ &= \int_{-1/2}^{1/2} e^{i2\pi fm} [\psi_{k,k'} \psi_{l,l'} G_{k,k',l,l'}(f) + \omega_{k,k'} \omega_{l,l'} S_{k,k',l,l'}(f)] \, df \\ &+ \int_{-1/2}^{1/2} e^{i2\pi fm} \int_{-1/2}^{1/2} G_{k,k',l,l'}(f - f') S_{k,k',l,l'}(f') \, df' \, df \\ &= \int_{-1/2}^{1/2} e^{i2\pi fm} \left[\psi_{k,k'} \psi_{l,l'} G_{k,k',l,l'}(f) + \omega_{k,k'} \omega_{l,l'} S_{k,k',l,l'}(f) \right. \\ &\quad \left. + \int_{-1/2}^{1/2} G_{k,k',l,l'}(f - f') S_{k,k',l,l'}(f') \, df' \right] \, df. \end{aligned}$$

It then follows that

$$\begin{aligned} & \text{cov} \{ Q_t, Q_{t+m} \} \\ &= \sum_{k,k'} \sum_{l,l'} a_{k,k'} a_{l,l'} \int_{-1/2}^{1/2} e^{i2\pi fm} \left[\psi_{k,k'} \psi_{l,l'} G_{k,k',l,l'}(f) + \omega_{k,k'} \omega_{l,l'} S_{k,k',l,l'}(f) \right. \\ &\quad \left. + \int_{-1/2}^{1/2} G_{k,k',l,l'}(f - f') S_{k,k',l,l'}(f') \, df' \right] \, df \end{aligned}$$

$$= \int_{-1/2}^{1/2} e^{i2\pi fm} \sum_{k,k'} \sum_{l,l'} a_{k,k'} a_{l,l'} \left[\psi_{k,k'} \psi_{l,l'} G_{k,k',l,l'}(f) + \omega_{k,k'} \omega_{l,l'} S_{k,k',l,l'}(f) + \int_{-1/2}^{1/2} G_{k,k',l,l'}(f-f') S_{k,k',l,l'}(f') df' \right] df,$$

which is independent of t and shows that $\{Q_t\}$ is a stationary process with SDF

$$S_Q(f) = \sum_{k,k'} \sum_{l,l'} a_{k,k'} a_{l,l'} [\psi_{k,k'} \psi_{l,l'} G_{k,k',l,l'}(f) + \omega_{k,k'} \omega_{l,l'} S_{k,k',l,l'}(f) + S * G_{k,k',l,l'}(f)],$$

where

$$S * G_{k,k',l,l'}(f) = \int_{-1/2}^{1/2} G_{k,k',l,l'}(f-f') S_{k,k',l,l'}(f') df'.$$

■

Proposition 16 *Let $\{X_t\}$ be a real-valued zero mean Gaussian stationary process with ACVS $s_{X,m}$ and SDF S_X that is square integrable over $[-\frac{1}{2}, \frac{1}{2}]$. Let $\{\delta_t\}$ be a binary-valued strictly stationary process that is independent of $\{X_t\}$ and satisfies Assumption 3. Let*

$$Z_{u,j,t} = \sum_{l=0}^{L_j-1} \sum_{l'=0}^{L_j-1} h_{j,l} h_{j,l'} \beta_{l-l'} X_{t-l} X_{t-l'} \delta_{t-l} \delta_{t-l'},$$

where $\beta_m^{-1} = \Pr[\delta_t = 1 \text{ and } \delta_{t+m} = 1]$. Then $\{Z_{u,j,t}\}$ is a second order stationary process whose ACVS are absolutely summable, i.e., SDF of $\{Z_{u,j,t}\}$ at zero is strictly positive.

Proof of Proposition 16 Let $U_{l,l',t} = X_{t-l} X_{t-l'}$, $\mathbf{U}_t = [U_{k,k',t}, U_{l,l',t}]^T$, $V_{l,l',t} = \delta_{t-l} \delta_{t-l'}$ and $a_{l,l'} = h_{j,l} h_{j,l'} \beta_{l-l'}$. By Proposition 11, \mathbf{U}_t has a continuous cross spectrum $S_{k,k',l,l'}$. By Lemma 15, the SDF of $\{Z_{u,j,t}\}$ is given by

$$S_{u,j}(f) = \sum_{k,k'} \sum_{l,l'} a_{k,k'} a_{l,l'} [\psi_{k,k'} \psi_{l,l'} G_{k,k',l,l'}(f) + \omega_{k,k'} \omega_{l,l'} S_{k,k',l,l'}(f) + S * G_{k,k',l,l'}(f)].$$

Note that in the above $\psi_{l,l'} = E X_{t-l} X_{t-l'}$, $\omega_{l,l'} = E \delta_{t-l} \delta_{t-l'}$ and the cross spectrum between $\delta_{t-k} \delta_{t-k'}$ and $\delta_{t-l} \delta_{t-l'}$, for any k, k', l and l' , is denoted by $G_{k,k',l,l'}$. Moreover, since $a_{l,l'} \omega_{l,l'} = h_{j,l} h_{j,l'}$, by Proposition 12

$$\sum_{k,k'} \sum_{l,l'} a_{k,k'} a_{l,l'} \omega_{k,k'} \omega_{l,l'} S_{k,k',l,l'}(0) = \sum_{k,k'} \sum_{l,l'} h_{j,k} h_{j,k'} h_{j,l} h_{j,l'} S_{k,k',l,l'}(0) > 0,$$

and hence $S_{u,j}(0) > 0$.

■

Proposition 17 Let $\{X_t\}$ be a real-valued Gaussian stationary process with zero mean, and SDF S_X that satisfies

$$\int_{-1/2}^{1/2} \sin^4(\pi f) S_X^2(f) df < \infty.$$

Let $\{\delta_t\}$ be a binary-valued strictly stationary process that is independent of $\{X_t\}$ and satisfies Assumption 3. Let

$$Z_{v,j,t} = -\frac{1}{2} \sum_{l=0}^{L_j-1} \sum_{l'=0}^{L_j-1} h_{j,l} h_{j,l'} \beta_{l-l'} (X_{t-l} - X_{t-l'})^2 \delta_{t-l} \delta_{t-l'},$$

where $\beta_m^{-1} = \Pr[\delta_t = 1 \text{ and } \delta_{t+m} = 1]$. Then $\{Z_{v,j,t}\}$ is a second order stationary process whose ACVS are absolutely summable, i.e., SDF of $\{Z_{v,j,t}\}$ at zero is strictly positive.

Proof of Proposition 17. The proof closely parallels that of Proposition 16. Let $U_{l,l',t} = -\frac{1}{2}(X_{t-l} - X_{t-l'})^2$, $\mathbf{U}_t = [U_{k,k',t}, U_{l,l',t}]^T$, $V_{l,l',t} = \delta_{t-l} \delta_{t-l'}$ and $a_{l,l'} = h_{j,l} h_{j,l'} \beta_{l-l'}$. By Proposition 13, \mathbf{U}_t has a continuous cross spectrum $S_{k,k',l,l'}$. By Lemma 15, the SDF of $\{Z_{v,j,t}\}$ is given by

$$S_{v,j}(f) = \sum_{k,k'} \sum_{l,l'} a_{k,k'} a_{l,l'} [\psi_{k,k'} \psi_{l,l'} G_{k,k',l,l'}(f) + \omega_{k,k'} \omega_{l,l'} S_{k,k',l,l'}(f) + S * G_{k,k',l,l'}(f)].$$

Note that in the above $\psi_{l,l'} = -\frac{1}{2} \mathbb{E}(X_{t-l} - X_{t-l'})^2$, $\omega_{l,l'} = \mathbb{E} \delta_{t-l} \delta_{t-l'}$ and the cross spectrum between $\delta_{t-k} \delta_{t-k'}$ and $\delta_{t-l} \delta_{t-l'}$, for any k, k', l and l' , is denoted by $G_{k,k',l,l'}$. Moreover, since $a_{l,l'} \omega_{l,l'} = h_{j,l} h_{j,l'}$, by Proposition 14

$$\sum_{k,k'} \sum_{l,l'} a_{k,k'} a_{l,l'} \omega_{k,k'} \omega_{l,l'} S_{k,k',l,l'}(0) = \sum_{k,k'} \sum_{l,l'} h_{j,k} h_{j,k'} h_{j,l} h_{j,l'} S_{k,k',l,l'}(0) > 0,$$

and hence $S_{v,j}(0) > 0$. ■

The following theorem is from Brillinger (1981, p. 21).

Theorem 18 Consider a two way array of random variables (RVs) $\Theta_{i,j}$, $j = 1, \dots, J_i$ and $i = 1, \dots, n$. Consider the n RVs $\Upsilon_i = \prod_{j=1}^{J_i} \Theta_{i,j}$ for $i = 1, \dots, n$. Then the joint cumulant of $\Upsilon_1, \dots, \Upsilon_n$ is given by the formula

$$\text{cum}(\Upsilon_1, \dots, \Upsilon_n) = \sum_{\chi} \text{cum}(\Theta_{i,j} : (i,j) \in \chi_1) \cdots \text{cum}(\Theta_{i,j} : (i,j) \in \chi_r)$$

where the summation is over all indecomposable partitions $\chi = \chi_1 \cup \cdots \cup \chi_r$ of the (not necessarily rectangular) two way table

$$\begin{array}{ccc} (1, 1) & \cdots & (1, J_1) \\ \vdots & & \vdots \\ (n, 1) & \cdots & (n, J_n). \end{array} \tag{17}$$

Lemma 19 Assume that $\{X_t\}$ satisfies the conditions stated in Theorem 5. Let $U_{p,t} = X_{t-l}X_{t-l'}$ and $\mathbb{E}U_{p,t} = \psi_p$, where $p = (l, l')$. Then for $n \geq 3$ and fixed p_1, \dots, p_n ,

$$\sum_{t_1, \dots, t_n} |\text{cum}(U_{p_1, t_1} - \psi_{p_1}, \dots, U_{p_n, t_n} - \psi_{p_n})| = o(M^{n/2}), \quad (18)$$

where each t_i ranges from 0 to $M - 1$.

Proof of Lemma 19. Since a cumulant is invariant under the addition of constants, we obtain

$$\text{cum}(U_{p_1, t_1} - \psi_{p_1}, \dots, U_{p_n, t_n} - \psi_{p_n}) = \text{cum}(U_{p_1, t_1}, \dots, U_{p_n, t_n}).$$

Consider the $n \times 2$ table of RVs given by

$$\begin{array}{cc} \Theta_{1,1} = X_{t_1-l_1} & \Theta_{1,2} = X_{t_1-l'_1} \\ \vdots & \vdots \\ \Theta_{n,1} = X_{t_n-l_n} & \Theta_{n,2} = X_{t_n-l'_n}. \end{array}$$

As $U_{p,t}$ is the product of the two Gaussian RVs in row p of the table, we invoke Theorem 18 to break up $\text{cum}(U_{p_1, t_1}, \dots, U_{p_n, t_n})$. Moreover, because of the Gaussian assumption, all r th order cumulants for $r \geq 3$ are zero, so we restrict ourselves to indecomposable partitions $\chi = \chi_1 \cup \dots \cup \chi_n$ of the two way table

$$\begin{array}{cc} (1, 1) & (1, 2) \\ \vdots & \vdots \\ (n, 1) & (n, 2). \end{array} \quad (19)$$

such that $|\chi_k| = 2$ for all k . Hence $\text{cum}(U_{p_1, t_1}, \dots, U_{p_n, t_n})$ is equal to

$$\sum_{\chi} \text{cum}(\Theta_{i,j} : (i, j) \in \chi_1) \cdots \text{cum}(\Theta_{i,j} : (i, j) \in \chi_n) \equiv \sum_{\chi} I_{U, M}(\chi).$$

It then suffices to show that $I_{U, M}(\chi) = o(M^{n/2})$ for any fixed χ . As χ is an indecomposable partition, without loss of generality, we can properly order the index of the table in (19) so that $\chi_i = \{(i, \eta_i), (i+1, \xi_{i+1})\}$ for $i = 1, \dots, n-1$ and $\chi_n = \{(n, \eta_n), (1, \xi_1)\}$, where η_i takes values of 1 or 2 for $i = 1, \dots, n$ and $\xi_k = 3 - \eta_k$. We set, for $k = 1, \dots, n$,

$$e_k = \begin{cases} l_{(k+1) \bmod n} - l_k & \text{if } \xi_{(k+1) \bmod n} = \eta_k = 1, \\ l'_{(k+1) \bmod n} - l_k & \text{if } \xi_{(k+1) \bmod n} = 2, \eta_k = 1, \\ l_{(k+1) \bmod n} - l'_k & \text{if } \xi_{(k+1) \bmod n} = 1, \eta_k = 2 \quad \text{and} \\ l'_{(k+1) \bmod n} - l'_k & \text{if } \xi_{(k+1) \bmod n} = \eta_k = 2. \end{cases}$$

Then we can write

$$\text{cum}(\Theta_{i,j} : (i, j) \in \chi_k) = s_{X, t_{k+1} - t_k - e_k}$$

for $k = 1, \dots, n-1$ and $\text{cum}(\Theta_{i,j} : (i,j) \in \chi_n) = s_{X,t_1-t_n-e_n}$. Hence

$$I_{U,M}(\chi) = \sum_{t_1, \dots, t_n} s_{X,t_1-t_n-e_n} \prod_{i=1}^{n-1} s_{X,t_{i+1}-t_i-e_i} \quad (20)$$

We write $I_{U,M}(\chi) = I'_{U,M}(\chi) + I''_{U,M}(\chi)$, where $I'_{U,M}(\chi)$ is the sum of (20) taken over t_i , $i = 1, \dots, n$ such that $|t_{i+1} - t_i| \leq K$ for $i = 1, \dots, n-1$ and $|t_1 - t_n| \leq K$. Set $q_i = t_{i+1} - t_i$ for $i = 1, \dots, n-1$. Since $s_{X,\tau}$ is bounded in magnitude by $s_{X,0}$, we obtain

$$|I'_{U,M}(\chi)| \leq s_{X,0} \sum_{|q_i| \leq K, i=1, \dots, n-1} \sum_{|t_n| \leq N} 1 \leq s_{X,0} K^{n-1} M.$$

The rest of the proof runs parallel to that of Lemma 6 of Giraitis & Surgailis (1985). Thus we show that $I''_{U,M}(\chi) \leq \epsilon(K)M^{n/2}$ where $\epsilon(K) \rightarrow 0$ as $K \rightarrow \infty$. We repeatedly use the Cauchy–Schwartz inequality to obtain

$$\begin{aligned} & I''_{U,M}(\chi) \\ &= \sum_{t_1, \dots, t_n} s_{X,t_1-t_n-e_n} \prod_{i=1}^{n-1} s_{X,t_{i+1}-t_i-e_i} \\ &= \sum_{t_1, \dots, t_{n-1}} \prod_{i=1}^{n-2} s_{X,t_{i+1}-t_i-e_i} \sum_{t_n} s_{X,t_1-t_n-e_n} s_{X,t_n-t_{n-1}-e_{n-1}} \\ &\leq \sum_{t_1, \dots, t_{n-1}} \prod_{i=1}^{n-2} s_{X,t_{i+1}-t_i-e_i} \left(\sum_{t_n} s_{X,t_1-t_n-e_n}^2 \right)^{\frac{1}{2}} \left(\sum_{t_n} s_{X,t_n-t_{n-1}-e_{n-1}}^2 \right)^{\frac{1}{2}} \\ &= \sum_{t_1, \dots, t_{n-2}} \prod_{i=1}^{n-3} s_{X,t_{i+1}-t_i-e_i} \left(\sum_{t_n} s_{X,t_1-t_n-e_n}^2 \right)^{\frac{1}{2}} \sum_{t_{n-1}} s_{X,t_{n-1}-t_{n-2}-e_{n-2}} \\ &\quad \left(\sum_{t_n} s_{X,t_n-t_{n-1}-e_{n-1}}^2 \right)^{\frac{1}{2}} \\ &\leq \sum_{t_1, \dots, t_{n-2}} \prod_{i=1}^{n-3} s_{X,t_{i+1}-t_i-e_i} \left(\sum_{t_n} s_{X,t_1-t_n-e_n}^2 \right)^{\frac{1}{2}} \left(\sum_{t_{n-1}} s_{X,t_{n-1}-t_{n-2}-e_{n-2}}^2 \right)^{\frac{1}{2}} \\ &\quad \left(\sum_{t_{n-1}, t_n} s_{X,t_n-t_{n-1}-e_{n-1}}^2 \right)^{\frac{1}{2}} \\ &\quad \vdots \\ &\leq \left(\sum_{t_1, t_n} s_{X,t_1-t_n-e_n}^2 \right)^{\frac{1}{2}} \prod_{i=2}^n \left(\sum_{t_{i-1}, t_i} s_{X,t_i-t_{i-1}-e_{i-1}}^2 \right)^{\frac{1}{2}} \end{aligned}$$

Now use that fact that t_i , $i = 1, \dots, n$ ranges from 0 to $M-1$ and $|t_{i+1} - t_i| > K$ for $i = 1, \dots, n-1$ and $|t_1 - t_n| > K$. Thus for example

$$\sum_{t_{i-1}, t_i} s_{X,t_i-t_{i-1}-e_{i-1}}^2 \leq \text{constant} \sum_{|\tau| > K} \sum_{t_i} s_{X,\tau}^2 = \text{constant} M \sum_{|\tau| > K} s_{X,\tau}^2,$$

where $\sum_{|\tau|>K} s_{X,\tau}^2$ goes to zero as $K \rightarrow \infty$. This is because $s_{X,\tau}$ is square summable. Hence we have

$$I''_{U,M}(\chi) \leq \text{constant } M^{\frac{1}{2}n} \left(\sum_{|\tau|>K} s_{X,\tau}^2 \right)^{\frac{1}{2}n} = \epsilon(K)M^{\frac{1}{2}n}$$

Hence we have the required result by choosing $K = \lfloor \log(M) \rfloor$. ■

Lemma 20 *Assume that $\{X_t\}$ satisfies the conditions stated in Theorem 7. Let $U_{p,t} = -\frac{1}{2}(X_{t-l} - X_{t-l'})^2$ and $\mathbb{E}U_{p,t} = \psi_p$, in which $p = (l, l')$. Then for $n \geq 3$ and fixed p_1, \dots, p_n ,*

$$\sum_{t_1, \dots, t_n} |\text{cum}(U_{p_1, t_1} - \psi_{p_1}, \dots, U_{p_n, t_n} - \psi_{p_n})| = o(M^{n/2}),$$

where each t_i ranges from 0 to $M - 1$.

The proof goes as that of Proposition 19 with the modification that $U_{p,t}$ can be written as the product of $X_{t-l} - X_{t-l'}$ and $-\frac{1}{2}(X_{t-l} - X_{t-l'})$, where the Gaussian process $X_{t-l} - X_{t-l'}$ has a square integrable SDF.

Lemma 21 *Let $\{U_{p,t}\}$ be as in Proposition 19 (or as in Proposition 20). Assume*

$$\kappa_n(p_1, \dots, p_n, t_1, \dots, t_n) = \text{cum}(U_{p_1, t_1} - \psi_{p_1}, \dots, U_{p_n, t_n} - \psi_{p_n})$$

Define for $i = 1, 2, \dots, n - 1$

$$\kappa_n(p_1, \dots, p_n, t_1, \dots, t_i) = \sum_{t_{i+1}, \dots, t_n} M^{-\frac{1}{2}(n-i-1)} \kappa_n(p_1, \dots, p_n, t_1, \dots, t_n),$$

where the summation in t_j is taken over 0 to $M - 1$. Then $\kappa_n(p_1, \dots, p_n, t_1, \dots, t_i)$ is bounded for $i = 1, 2, \dots, n$ and satisfies

$$\sum_{t_1, \dots, t_i} \kappa_n(p_1, \dots, p_n, t_1, \dots, t_i) = o(M^{\frac{1}{2}(i+1)}), \quad (21)$$

where each t_j ranges from 0 to $M - 1$.

Proof of Lemma 21. We retain all the notation of Proposition 19. Thus

$$\kappa_n(p_1, \dots, p_n, t_1, \dots, t_n) = \sum_{\chi} \text{cum}(\Theta_{i,j} : (i, j) \in \chi_1) \cdots \text{cum}(\Theta_{i,j} : (i, j) \in \chi_n).$$

It then suffices to show that for any fixed χ

$$\sum_{t_{i+1}, \dots, t_n} M^{-\frac{1}{2}(n-i-1)} \text{cum}(\Theta_{i,j} : (i, j) \in \chi_1) \cdots \text{cum}(\Theta_{i,j} : (i, j) \in \chi_n) \quad (22)$$

is bounded. Note that equation (21) then simply follows from equation (18). As in Proposition 19, we rearrange the indices in the table in (19). Then

$$\text{cum}(\Theta_{i,j} : (i,j) \in \chi_1) \cdots \text{cum}(\Theta_{i,j} : (i,j) \in \chi_n) = s_{X,t_1-t_n-e_n} \prod_{i=1}^{n-1} s_{X,t_{i+1}-t_i-e_i}.$$

Hence by equation (22) it suffices to show that

$$\sum_{t_{\lambda_1}, \dots, t_{\lambda_i}} M^{-\frac{1}{2}(i-1)} s_{X,t_1-t_n-e_n} \prod_{i=1}^{n-1} s_{X,t_{i+1}-t_i-e_i} \quad (23)$$

is bounded for any choice of $\lambda_1, \dots, \lambda_i$ that belong to $1, \dots, n$ and $i < n$.

Consider $i = 1$. WLOG assume $\lambda_1 = n$. Then

$$\begin{aligned} & \sum_{t_n} s_{X,t_1-t_n-e_n} \prod_{i=1}^{n-1} s_{X,t_{i+1}-t_i-e_i} \\ & \leq \prod_{i=1}^{n-2} s_{X,t_{i+1}-t_i-e_i} \left(\sum_{t_n} s_{X,t_1-t_n-e_n}^2 \right)^{\frac{1}{2}} \left(\sum_{t_n} s_{X,t_n-t_{n-1}-e_{n-1}}^2 \right)^{\frac{1}{2}}, \end{aligned}$$

which is bounded because of the square integrability assumption. Thus (23) is bounded.

Now consider $i = 2$. WLOG assume $\lambda_1 = n$. Now we have two cases. In the first case $\lambda_2 = 1$ or $n - 1$ so that the pair $t_{\lambda_1}, t_{\lambda_2}$ appears together in a single term involving s_X in (23). If we assume WLOG $\lambda_2 = n - 1$ we obtain

$$\begin{aligned} & \sum_{t_{n-1}, t_n} M^{-\frac{1}{2}} s_{X,t_1-t_n-e_n} \prod_{i=1}^{n-1} s_{X,t_{i+1}-t_i-e_i} \\ & \leq \sum_{t_{n-1}} M^{-\frac{1}{2}} \prod_{i=1}^{n-2} s_{X,t_{i+1}-t_i-e_i} \left(\sum_{t_n} s_{X,t_1-t_n-e_n}^2 \right)^{\frac{1}{2}} \left(\sum_{t_n} s_{X,t_n-t_{n-1}-e_{n-1}}^2 \right)^{\frac{1}{2}} \\ & \leq \prod_{i=1}^{n-3} s_{X,t_{i+1}-t_i-e_i} \left(\sum_{t_n} s_{X,t_1-t_n-e_n}^2 \right)^{\frac{1}{2}} \left(\sum_{t_{n-1}} s_{X,t_{n-1}-t_{n-2}-e_{n-2}}^2 \right)^{\frac{1}{2}} \\ & \quad \left(M^{-1} \sum_{t_{n-1}, t_n} s_{X,t_n-t_{n-1}-e_{n-1}}^2 \right)^{\frac{1}{2}} \end{aligned}$$

Clearly the above expression is bounded since $\sum_t s_{X,t}^2$ is, and therefore

$$\lim_{M \rightarrow \infty} M^{-1} \sum_{t_{n-1}, t_n} s_{X,t_n-t_{n-1}-e_{n-1}}^2 = \sum_{\tau} s_{X,\tau-e_{n-1}}^2 < \infty.$$

Thus (23) is bounded. In the second case assume $\lambda_2 = n - 2$. Thus $t_{\lambda_1}, t_{\lambda_2}$ appear in two distinct terms involving s_X in (23). Hence

$$\sum_{t_{n-2}, t_n} s_{X,t_1-t_n-e_n} \prod_{i=1}^{n-1} s_{X,t_{i+1}-t_i-e_i}$$

$$\begin{aligned}
&\leq \sum_{t_{n-2}} \prod_{i=1}^{n-2} s_{X,t_{i+1}-t_i-e_i} \left(\sum_{t_n} s_{X,t_1-t_n-e_n}^2 \right)^{\frac{1}{2}} \left(\sum_{t_n} s_{X,t_n-t_{n-1}-e_{n-1}}^2 \right)^{\frac{1}{2}} \\
&\leq \prod_{i=1}^{n-4} s_{X,t_{i+1}-t_i-e_i} \left(\sum_{t_n} s_{X,t_1-t_n-e_n}^2 \right)^{\frac{1}{2}} \left(\sum_{t_n} s_{X,t_n-t_{n-1}-e_{n-1}}^2 \right)^{\frac{1}{2}} \\
&\quad \left(\sum_{t_{n-1}} s_{X,t_{n-1}-t_{n-2}-e_{n-2}}^2 \right)^{\frac{1}{2}} \left(\sum_{t_{n-2}} s_{X,t_{n-2}-t_{n-3}-e_{n-3}}^2 \right)^{\frac{1}{2}}
\end{aligned}$$

Clearly this is bounded. Note that we do not need to use the $M^{-\frac{1}{2}}$ factor. Thus boundedness of (23) holds.

The pattern for the general proof is now clear. Note that, because χ is an indecomposable partition, there can be at most $i-1$ pairs of λ_i , namely $(\lambda_j, \lambda_{j+1})$ for $j = 1, \dots, i-1$ such that each of $(i-1)$ pairs $(t_{\lambda_j}, t_{\lambda_{j+1}})$ appears in distinct $i-1$ terms involving s_X in the equation (23). Thus summing over t_{λ_j} for $j = 1, \dots, i$ in the left hand side of (23) and repeated use of Cauchy–Schwartz inequality will give rise to the $(i-1)$ terms $M^{-1} \sum_{t_{\lambda_j}, t_{\lambda_{j+1}}} s_{X,t_{\lambda_{j+1}}-t_{\lambda_j}-e_{\lambda_j}}^2$, $j = 1, \dots, i-1$. Note that all these terms are bounded and hence boundedness of (23) follows. Of course, if there are less than $(i-1)$ such pairs $(\lambda_j, \lambda_{j+1})$, we no longer need to use the factor $M^{-\frac{1}{2}(i-1)}$ (in fact in the exponent we just need half the number of such pairs). This completes the proof. \blacksquare

Proof of Theorem 5. Take $U_{p,t} = X_{t-l}X_{t-l'}$, $V_{p,t} = \delta_{t-l}\delta_{t-l'}$ and $a_p = h_{j,l}h_{j,l'}\beta_{l-l'}$, where $p = (l, l')$. As in Lemma 1, take $Q_t = \sum_p a_p (U_{p,t}V_{p,t} - \psi_p\omega_p)$. Note that $\hat{u}_X(\tau_j) - \nu_X^2(\tau_j)$ is the average of Q_t over $L_j - 1 \leq t \leq N - 1$ with $\beta_{l-l'}$ replaced by its consistent estimate $\hat{\beta}_{l,l'}$. Since Q_t is stationary, we first prove a CLT for $R = M^{-\frac{1}{2}} \sum_{t=0}^{M-1} Q_t$ and then invoke Slutsky's theorem to complete the proof that $\hat{u}_X(\tau_j)$ is asymptotically normal. We use Žurbenko (1986), p. 2 to write down the log of the characteristic function of R as

$$\log F(\lambda) = \sum_{n=1}^{\infty} \frac{i^n \lambda^n}{n!} \sum_{t_1, \dots, t_n} \frac{B_n(t_1, \dots, t_n)}{M^{n/2}},$$

where B_n is the n th order cumulant of Q_t , and each t_i ranges from 0 to $M-1$. Since Q_t is centered, $B_1(t_1) = 0$. By Proposition 16, the auto-covariances $s_{Q,\tau}$ of Q_t are absolutely summable and $M^{-1} \sum_{t_1} \sum_{t_2} B_2(t_1, t_2) \rightarrow \sum_{\tau} s_{Q,\tau} = S_Q(0) > 0$. In order to prove the CLT for R , it suffices to show that $\sum_{t_1, \dots, t_n} M^{-n/2} B_n(t_1, \dots, t_n) \rightarrow 0$ for $n = 3, 4, \dots$

First using p. 19 of Brillinger (1981), we break up the n th order cumulant as follows:

$$\begin{aligned}
B_n(t_1, \dots, t_n) &= \sum_{p_1} \cdots \sum_{p_n} a_{p_1} \cdots a_{p_n} \\
&\quad \text{cum}(U_{p_1, t_1} V_{p_1, t_1} - \psi_{p_1} \omega_{p_1}, \dots, U_{p_n, t_n} V_{p_n, t_n} - \psi_{p_n} \omega_{p_n}).
\end{aligned}$$

Let $D_{1,p,t} = (U_{p,t} - \psi_p)(V_{p,t} - \omega_p)$, $D_{2,p,t} = \omega_p(U_{p,t} - \psi_p)$ and $D_{3,p,t} = \psi_p(V_{p,t} - \omega_p)$. Then $U_{p,t}V_{p,t} - \psi_p\omega_p = D_{1,p,t} + D_{2,p,t} + D_{3,p,t}$. Using p. 19 of Brillinger (1981) again, we have

$$\text{cum}(U_{p_1, t_1} V_{p_1, t_1} - \psi_{p_1} \omega_{p_1}, \dots, U_{p_n, t_n} V_{p_n, t_n} - \psi_{p_n} \omega_{p_n})$$

$$= \sum_{c_1, \dots, c_n} \text{cum}(D_{c_1, p_1, t_1}, \dots, D_{c_n, p_n, t_n}),$$

where each c_i ranges from 1 to 3. Therefore, it suffices to show that, for fixed p_1, \dots, p_n and c_1, \dots, c_n , $\text{cum}(D_{c_1, p_1, t_1}, \dots, D_{c_n, p_n, t_n}) = o(M^{n/2})$. Since the cumulant of n variables is invariant under a reordering of the variables, assume $c_1 = c_2 = \dots = c_m = 1, c_{m+1} = c_{m+2} = \dots = c_{m'} = 2, c_{m'+1} = c_{m'+2} = \dots = c_n = 3$, and consider a two way table $\Theta_{i,j}$ with n rows. Rows $i = 1, \dots, m$ each contain exactly two RVs, namely, $U_{p_i, t_i} - \psi_{p_i}$ and $V_{p_i, t_i} - \omega_{p_i}$ (note that the product of the RVs in row i is D_{1, p_i, t_i}). The remaining $n - m$ rows contain one RV each, namely, $U_{p_i, t_i} - \psi_{p_i}$ (which is proportional to D_{2, p_i, t_i} for $i = (m + 1), \dots, m'$, and $V_{p_i, t_i} - \omega_{p_i}$ (proportional to D_{3, p_i, t_i}) for $i = m' + 1, \dots, n$. Thus the two way table of $\Theta_{i,j}$ is given by

$$\begin{aligned} \Theta_{1,1} &= U_{p_1, t_1} - \psi_{p_1}, & \Theta_{1,2} &= V_{p_1, t_1} - \omega_{p_1}, \\ \vdots & & \vdots & \\ \Theta_{m,1} &= U_{p_m, t_m} - \psi_{p_m}, & \Theta_{m,2} &= V_{p_m, t_m} - \omega_{p_m}, \\ \Theta_{m+1,1} &= V_{p_{m+1}, t_{m+1}} - \omega_{p_{m+1}}, & & \\ \vdots & & & \\ \Theta_{m',1} &= V_{p_{m'}, t_{m'}} - \omega_{p_{m'}}, & & \\ \Theta_{m'+1,1} &= U_{p_{m'+1}, t_{m'+1}} - \psi_{p_{m'+1}}, & & \\ \vdots & & & \\ \Theta_{n,1} &= U_{p_n, t_n} - \psi_{p_n}. \end{aligned}$$

Theorem 18 now yields

$$\text{cum}(D_{c_1, p_1, t_1}, \dots, D_{c_n, p_n, t_n}) \propto \sum_{\chi} \text{cum}(\Theta_{i,j} : (i, j) \in \chi_1) \cdots \text{cum}(\Theta_{i,j} : (i, j) \in \chi_r).$$

We complete the proof by showing that for any fixed χ

$$\sum_{t_1, \dots, t_n} \text{cum}(\Theta_{i,j} : (i, j) \in \chi_1) \cdots \text{cum}(\Theta_{i,j} : (i, j) \in \chi_r) = o(M^{n/2}). \quad (24)$$

We prove the above in the following steps.

Step 1: Since $\Theta_{i,j}$ is centered, its first order cumulant is zero, so we can restrict ourselves to cases where $|\chi_k| \geq 2$ for all k . If any group of RVs in $\Theta_{i,j} : (i, j) \in \chi_k$ is independent of the remaining RVs in that set, then $\text{cum}(\Theta_{i,j} : (i, j) \in \chi_k) = 0$. Since $U_{p_i, t_i} - \psi_{p_i}$'s and $V_{p_i, t_i} - \omega_{p_i}$'s are independent, we need only consider χ_k containing either just $U_{p_i, t_i} - \psi_{p_i}$'s or just $V_{p_i, t_i} - \omega_{p_i}$'s.

Step 2: Consider $m = 0$. In this case each row in $\Theta_{i,j}$ has only one RV, and thus all of $\Theta_{i,j}$ together form the only indecomposable partition $\chi = \chi_1$. Now if $m' = 0$, then by Assumption 3

$$\sum_{t_1, \dots, t_n} \text{cum}(\Theta_{i,j} : (i, j) \in \chi) = \sum_{t_1, \dots, t_n} \text{cum}(V_{p_1, t_1} - \omega_{p_1}, \dots, V_{p_n, t_n} - \omega_{p_n}) = o(M^{n/2}).$$

On the other hand if $m' = n$, then by Proposition 19

$$\sum_{t_1, \dots, t_n} \text{cum}(\Theta_{i,j} : (i, j) \in \chi) = \sum_{t_1, \dots, t_n} \text{cum}(U_{p_1, t_1} - \psi_{p_1}, \dots, U_{p_n, t_n} - \psi_{p_n}) = o(M^{n/2}).$$

Finally we rule out the case $1 \leq m' < n$ because then χ contains both $U_{p_i, t_i} - \psi_{p_i}$'s and $V_{p_i, t_i} - \omega_{p_i}$'s and hence $\text{cum}(\Theta_{i,j} : (i,j) \in \chi) = 0$.

Step 3: Finally consider $m \geq 1$. Assume that χ_1, \dots, χ_q partition $\Theta_{1,1}, \dots, \Theta_{m',1}$ (these are all $U_{p_i, t_i} - \psi_{p_i}$) and that $\chi_{q+1}, \dots, \chi_r$ partition $\Theta_{1,2}, \dots, \Theta_{m,2}, \Theta_{m'+1,1}, \dots, \Theta_{n,1}$ (these are all $V_{p_i, t_i} - \omega_{p_i}$). To check (24) holds we need to consider five cases.

Case 1: When $m' > m$ we sum over $t_{m+1}, \dots, t_{m'}$ in the left hand side of (24). In order to keep track of all the individual t_i for which $(i, 1)$ belongs to χ_k for $k = 1, \dots, q$, we set $0 = \rho_0 \leq \rho_1 \leq \dots \leq \rho_q = m$, $m = \sigma_0 \leq \sigma_1 \leq \dots \leq \sigma_q = m'$. Assume $\chi_1 = \{(1 = \rho_0 + 1, 1), \dots, (\rho_1, 1), (m + 1 = \sigma_0 + 1, 1), \dots, (\sigma_1, 1)\}$, $\chi_2 = \{(\rho_1 + 1, 1), \dots, (\rho_2, 1), (\sigma_1 + 1, 1), \dots, (\sigma_2, 1)\}$, \dots , $\chi_q = \{(\rho_{q-1} + 1, 1), \dots, (\rho_q, 1), (\sigma_{q-1} + 1, 1), \dots, (\sigma_q, 1)\}$. Then, for $k = 1, \dots, q$, we obtain by Proposition 21

$$\begin{aligned} & \sum_{t_{\sigma_{k-1}+1}, \dots, t_{\sigma_k}} \text{cum}(\Theta_{i,j} : (i,j) \in \chi_k) \\ &= \sum_{t_{\sigma_{k-1}+1}, \dots, t_{\sigma_k}} \kappa_{\rho_k + \sigma_k - \rho_{k-1} - \sigma_{k-1}}(p_i, t_i : (i, 1) \in \chi_k) \\ &= M^{\frac{1}{2}(\sigma_k - \sigma_{k-1} - 1)^+} \kappa_{\rho_k + \sigma_k - \rho_{k-1} - \sigma_{k-1}}(p_i, (i, 1) \in \chi_k, t_{\rho_{k-1}+1}, \dots, t_{\rho_k}). \end{aligned}$$

Thus summing over $t_{m+1}, \dots, t_{m'}$ in the left hand side of (24) gives

$$\begin{aligned} & \sum_{t_1, \dots, t_n} \text{cum}(\Theta_{i,j} : (i,j) \in \chi_1) \cdots \text{cum}(\Theta_{i,j} : (i,j) \in \chi_r) \\ &= \sum_{t_1, \dots, t_m} \sum_{t_{m'+1}, \dots, t_n} \text{cum}(\Theta_{i,j} : (i,j) \in \chi_{q+1}) \cdots \text{cum}(\Theta_{i,j} : (i,j) \in \chi_r) \\ &\times \sum_{t_{m+1}, \dots, t_{m'}} \text{cum}(\Theta_{i,j} : (i,j) \in \chi_1) \cdots \text{cum}(\Theta_{i,j} : (i,j) \in \chi_q) \\ &= \sum_{t_1, \dots, t_m} \sum_{t_{m'+1}, \dots, t_n} \text{cum}(\Theta_{i,j} : (i,j) \in \chi_{q+1}) \cdots \text{cum}(\Theta_{i,j} : (i,j) \in \chi_r) \\ &\times \prod_{k=1}^q M^{\frac{1}{2}(\sigma_k - \sigma_{k-1} - 1)^+} \kappa_{\rho_k + \sigma_k - \rho_{k-1} - \sigma_{k-1}}(p_i, (i, 1) \in \chi_k, t_{\rho_{k-1}+1}, \dots, t_{\rho_k}) \end{aligned}$$

Now use boundedness of $\kappa_{\rho_k + \sigma_k - \rho_{k-1} - \sigma_{k-1}}(p_i, (i, 1) \in \chi_k, t_{\rho_{k-1}+1}, \dots, t_{\rho_k})$ (Proposition 21), boundedness of the cumulant of $\Theta_{i,j}$ and the fact that $n > m'$ to obtain

$$\begin{aligned} & \sum_{t_1, \dots, t_n} \text{cum}(\Theta_{i,j} : (i,j) \in \chi_1) \cdots \text{cum}(\Theta_{i,j} : (i,j) \in \chi_r) \\ &\leq C_* M^{\frac{1}{2}(n - m' - 1)} \sum_{t_1, \dots, t_m} \sum_{t_{m'+1}, \dots, t_n} \text{cum}(\Theta_{i,j} : (i,j) \in \chi_{q+1}) \cdots \text{cum}(\Theta_{i,j} : (i,j) \in \chi_r) \\ &= M^{\frac{1}{2}(n - m' - 1)} O(M^{(m+n-m')/2}) = o(M^{n/2}). \end{aligned}$$

Here the last equality holds since $\frac{1}{2}(n - m' - 1) + \frac{1}{2}(m + n - m') = n - m' + \frac{1}{2}(m - 1) < n$ by virtue of the fact that $m' > m$.

Case 2: If $m' = m$ and $|\chi_k| > 2$ for some k in $q + 1, \dots, r$, then using the boundedness of $\text{cum}(\Theta_{i,j} : (i, j) \in \chi_{k'})$ for $k' = 1, \dots, q$, we obtain

$$\begin{aligned} & \sum_{t_1, \dots, t_n} \text{cum}(\Theta_{i,j} : (i, j) \in \chi_1) \cdots \text{cum}(\Theta_{i,j} : (i, j) \in \chi_r) \\ & \leq \text{constant} \sum_{t_1, \dots, t_n} \text{cum}(\Theta_{i,j} : (i, j) \in \chi_{q+1}) \cdots \text{cum}(\Theta_{i,j} : (i, j) \in \chi_r) = o(M^{n/2}). \end{aligned}$$

Here the last equality follows from Assumption 3.

Case 3: Consider $m = m'$ and $|\chi_k| = 2$ for $k = q + 1, \dots, r$. Clearly $2m > n > m$ and $r - q = n - m$. Let $(m + i, 1)$ be contained in χ_{q+i} for $i = 1, \dots, n$. Note that, by Assumption 3, $\sum_{t_i} \text{cum}(V_{p_i, t_i}, V_{p_\tau, t_\tau})$ is bounded for any fixed τ . Hence, for $i = 1, \dots, n - m$, $\sum_{t_{m+i}} \text{cum}(\Theta_{i,j} : (i, j) \in \chi_{q+i})$ is bounded. Now summing out t_{m+1}, \dots, t_n yields

$$\begin{aligned} & \sum_{t_1, \dots, t_n} \text{cum}(\Theta_{i,j} : (i, j) \in \chi_1) \cdots \text{cum}(\Theta_{i,j} : (i, j) \in \chi_r) \\ & = \sum_{t_1, \dots, t_n} \text{cum}(\Theta_{i,j} : (i, j) \in \chi_1) \cdots \text{cum}(\Theta_{i,j} : (i, j) \in \chi_q) \\ & \quad \text{cum}(\Theta_{i,j} : (i, j) \in \chi_{q+1}) \cdots \text{cum}(\Theta_{i,j} : (i, j) \in \chi_r) \\ & = \sum_{t_1, \dots, t_m} \text{cum}(\Theta_{i,j} : (i, j) \in \chi_1) \cdots \text{cum}(\Theta_{i,j} : (i, j) \in \chi_q) \\ & \quad \text{cum}(\Theta_{i,j} : (i, j) \in \chi_{q+n-m+1}) \cdots \text{cum}(\Theta_{i,j} : (i, j) \in \chi_r) \\ & \quad \sum_{t_{m+1}} \text{cum}(\Theta_{i,j} : (i, j) \in \chi_{q+1}) \cdots \sum_{t_n} \text{cum}(\Theta_{i,j} : (i, j) \in \chi_{q+n-m}) \\ & \leq \text{constant} \sum_{t_1, \dots, t_m} \text{cum}(\Theta_{i,j} : (i, j) \in \chi_1) \cdots \text{cum}(\Theta_{i,j} : (i, j) \in \chi_q) \\ & \quad \text{cum}(\Theta_{i,j} : (i, j) \in \chi_{q+n-m+1}) \cdots \text{cum}(\Theta_{i,j} : (i, j) \in \chi_r) \end{aligned}$$

Now use boundedness of $\text{cum}(\Theta_{i,j} : (i, j) \in \chi_k)$ for $k = q + n - m + 1, \dots, r$ and the fact that $n - m > m$ to derive

$$\begin{aligned} & \sum_{t_1, \dots, t_n} \text{cum}(\Theta_{i,j} : (i, j) \in \chi_1) \cdots \text{cum}(\Theta_{i,j} : (i, j) \in \chi_r) \\ & \leq \text{constant} \sum_{t_1, \dots, t_m} \text{cum}(\Theta_{i,j} : (i, j) \in \chi_1) \cdots \text{cum}(\Theta_{i,j} : (i, j) \in \chi_q) \\ & \quad \text{cum}(\Theta_{i,j} : (i, j) \in \chi_{q+n-m+1}) \cdots \text{cum}(\Theta_{i,j} : (i, j) \in \chi_r) \\ & \leq \text{constant} \sum_{t_1, \dots, t_m} \text{cum}(\Theta_{i,j} : (i, j) \in \chi_1) \cdots \text{cum}(\Theta_{i,j} : (i, j) \in \chi_q) = o(M^{n/2}). \end{aligned}$$

The last equality follows from 18. In the above derivation, the constant is changing from line to line.

Case 4: Consider $n = m$. Again if any $|\chi_k| > 2$ for $k = 1, \dots, q$, we are done by using (18) and the fact that cumulant of $V_{p_i, t_i} - \omega_{p_i}$ is bounded. More precisely,

$$\sum_{t_1, \dots, t_m} \text{cum}(\Theta_{i,j} : (i, j) \in \chi_1) \cdots \text{cum}(\Theta_{i,j} : (i, j) \in \chi_q)$$

$$\begin{aligned}
& \text{cum}(\Theta_{i,j} : (i,j) \in \chi_{q+1}) \cdots \text{cum}(\Theta_{i,j} : (i,j) \in \chi_r) \\
\leq & \text{constant} \sum_{t_1, \dots, t_m} \text{cum}(\Theta_{i,j} : (i,j) \in \chi_1) \cdots \text{cum}(\Theta_{i,j} : (i,j) \in \chi_q) \\
= & o(M^{m/2}).
\end{aligned}$$

Case 5: The last case is $n = m$ and all $|\chi_k| = 2$. Here the two way table of $\Theta_{i,j}$ is given by

$$\begin{aligned}
\Theta_{1,1} &= U_{p_1, t_1} - \psi_{p_1}, & \Theta_{1,2} &= V_{p_1, t_1} - \omega_{p_1}, \\
\vdots & & \vdots & \\
\Theta_{m,1} &= U_{p_m, t_m} - \psi_{p_m}, & \Theta_{m,2} &= V_{p_m, t_m} - \omega_{p_m}.
\end{aligned}$$

We reorder the indices and assume WLOG that $\chi_1 = \{(1, 1), (2, 1)\}$, $\chi_2 = \{(3, 1), (4, 1)\}$, \dots , $\chi_q = \{(m-1, 1), (m, 1)\}$ and $\chi_{q+1} = \{(1, 2), (3, 2)\}$, $\chi_{q+2} = \{(2, 2), (5, 2)\}$, $\chi_{q+3} = \{(4, 2), (7, 2)\}$, \dots , $\chi_{r-1} = \{(m-4, 2), (m-1, 2)\}$, and finally $\chi_r = \{(m-2, 2), (m, 2)\}$. Let $s_{U, p_i, p_{i'}}(t_i - t_{i'}) = \text{cov}(U_{p_i, t_i}, U_{p_{i'}, t_{i'}})$ and $s_{V, p_i, p_{i'}}(t_i - t_{i'}) = \text{cov}(V_{p_i, t_i}, V_{p_{i'}, t_{i'}})$. Now invoke Theorem 18 to write down

$$\begin{aligned}
& \sum_{t_1, \dots, t_m} \text{cum}(\Theta_{i,j} : (i,j) \in \chi_1) \cdots \text{cum}(\Theta_{i,j} : (i,j) \in \chi_r) \\
= & \sum_{t_1, \dots, t_m} \prod_{i=1}^q s_{U, p_{2i-1}, p_{2i}}(t_{2i-1} - t_{2i}) s_{V, p_1, p_3}(t_1 - t_3) s_{V, p_{m-2}, p_m}(t_{m-2} - t_m) \\
& \prod_{i=1}^{q-2} s_{V, p_{2i}, p_{2i+3}}(t_{2i} - t_{2i+3}).
\end{aligned}$$

Now let $k_{2i} = t_{2i-1} - t_{2i}$ for $i = 1, \dots, q$, $k_1 = t_1 - t_3$, $k_{2i+1} = t_{2i} - t_{2i+3}$ for $i = 1, \dots, q-2$. Then we can write $t_{m-2} - t_m$ in terms of k_1, \dots, k_{m-1} . Now change of indices implies

$$\begin{aligned}
& \sum_{t_1, \dots, t_m} \text{cum}(\Theta_{i,j} : (i,j) \in \chi_1) \cdots \text{cum}(\Theta_{i,j} : (i,j) \in \chi_r) \\
= & \sum_{k_1, \dots, k_{m-1}} \prod_{i=1}^q s_{U, p_{2i-1}, p_{2i}}(k_{2i}) s_{V, p_1, p_3}(k_1) s_{V, p_{m-2}, p_m}(t_{m-2} - t_m) \prod_{i=1}^{q-2} s_{V, p_{2i}, p_{2i+3}}(k_{2i+1}) \\
\leq & \sum_{k_1, \dots, k_{m-1}} \prod_{i=1}^q s_{U, p_{2i-1}, p_{2i}}(k_{2i}) s_{V, p_1, p_3}(k_1) \prod_{i=1}^{q-2} s_{V, p_{2i}, p_{2i+3}}(k_{2i+1}) < \infty.
\end{aligned}$$

The last inequality follows trivially from the absolute summability of $s_{U, p_i, p_{i'}}(k_i)$ and $s_{V, p_i, p_{i'}}(k_i)$. Hence we are done. \blacksquare

Proof of Theorem 7 Take $U_{l, l', t} = -\frac{1}{2}(X_{t-l} - X_{t-l'})^2$, $V_{l, l', t} = \delta_{t-l} \delta_{t-l'}$ and $a_{l, l'} = h_{j, l} h_{j, l'} \beta_{l-l'}$. Complete the proof as in Theorem 5 by checking all the steps. \blacksquare

Acknowledgements

This research was supported by the U.S. National Science Foundation under Grant No. DMS 0222115. Any opinions, findings, and conclusions or recommendations expressed in this material are those of the author(s) and do not necessarily reflect the views of the National Science Foundation. The authors thank Peter Guttorp and Chris Bretherton for discussions.

References

- Beran, J. (1994). *Statistics for long-memory processes*. New York: Chapman and Hall.
- Blackman, R. B., Tukey, J. W. (1958). *The measurement of power spectra*. New York: Dover Publications.
- Breuer, P., Major, P. (1983). Central limit theorems for nonlinear functionals of Gaussian fields. *Journal of Multivariate Analysis* 13, 425–441.
- Brillinger, D. R. (1981). *Time series*. Oakland, CA: Holden-Day Inc.
- Bronez, T. P. (1988). Spectral estimation of irregularly sampled multidimensional processes by generalized prolate spheroidal sequences. *IEEE Transactions on Acoustics, Speech, and Signal Processing* 36, 1862–1873.
- Candès, E. J., Donoho, D. L. (2002). Recovering edges in ill-posed inverse problems: optimality of curvelet frames. *The Annals of Statistics* 30, 784–842.
- Chiann, C., Morettin, P. A. (1998). A wavelet analysis for time series. *Nonparametric Statistics* 10, 1–46.
- Craigmile, P. F., Percival, D. B. (2005). Asymptotic decorrelation of between-scale wavelet coefficients. *IEEE Transactions on Information Theory* 51, 1039–1048.
- Daubechies, I. (1992). *Ten lectures on wavelets*. Philadelphia: SIAM.
- Donoho, D. L., Johnstone, I. M. (1998). Minimax estimation via wavelet shrinkage. *The Annals of Statistics* 26, 879–921.
- Donoho, D. L., Johnstone, I. M., Kerkyacharian, G., Picard, D. (1995). Wavelet shrinkage: asymptopia? *Journal of the Royal Statistical Society. Series B. Methodological* 57, 301–369.
- Feller, W. (1966). *An introduction to probability theory and its applications: volume II*. New York: John Wiley.
- Foster, G. (1996). Wavelets for period analysis of unevenly sampled time series. *The Astronomical Journal* 112, 1709–1729.
- Fox, R., Taqqu, M. S. (1987). Central limit theorems for quadratic forms in random variables having long-range dependence. *Probability Theory and Related Fields* 74, 213–240.

- Frick P., Grossmann, A., Tchamitchian P. (1998). Wavelet analysis of signals with gaps. *Journal of Mathematical Physics* 39, 4091–4107.
- Genovese, C. R., Wasserman, L. (2005). Confidence sets for nonparametric wavelet regression. *The Annals of Statistics* 33, 698–729.
- Giraitis, L., Surgailis, D. (1985). CLT and other limit theorems for functionals of Gaussian processes. *Zeitschrift für Wahrscheinlichkeitstheorie und Verwandte Gebiete* 70, 191–212.
- Giraitis, L., Taqqu, M. S. (1998). Central limit theorems for quadratic forms with time-domain conditions. *The Annals of Probability* 26, 377–398.
- Granger, C. W. J., Joyeux, R. (1980). An introduction to long-memory time series models and fractional differencing. *Journal of Time Series Analysis* 1, 15–29.
- Greenhall, C. A., Howe, D. A., Percival, D. B. (1999). Total variance, an estimator of long-term frequency stability. *IEEE Transactions on Ultrasonics, Ferroelectrics, and Frequency Control* 46, 1183–1191.
- Hall, P., Penev, S. (2004). Wavelet-based estimation with multiple sampling rates. *The Annals of Statistics* 32, 1933–1956.
- Ho, H. C., Sun, T. C. (1987). A central limit theorem for noninstantaneous filters of a stationary Gaussian process. *Journal of Multivariate Analysis* 22, 144–155.
- Hosking, J. R. M. (1981). Fractional differencing. *Biometrika* 68, 165–176.
- Isserlis, L. (1918). Formulae for determining the near values of products of deviations of mixed moment coefficients. *Biometrika* 12, 183–184.
- Kalifa, J., Mallat, S. (2003). Thresholding estimators for linear inverse problems and deconvolutions. *The Annals of Statistics* 31, 58–109.
- Labat, D., Ababou, R., Mangin, A. (2001). Introduction of wavelet analyses to rainfall/runoffs relationship for a karstic basin: the case of licq–atherey karstic system (France). *Ground Water* 39, 605–615.
- Lark, R. M., Webster, R. (2001). Changes in variance and correlation of soil properties with scale and location: analysis using an adapted maximal overlap discrete wavelet transform. *European Journal of Soil Science* 52, 547–562.
- Massel, S. R. (2001). Wavelet analysis for processing of ocean surface wave records. *Ocean Engineering* 28, 957–987.
- Nason, G. P., von Sachs, R., Kroisandt, G. (2000). Wavelet processes and adaptive estimation of the evolutionary wavelet spectrum. *Journal of the Royal Statistical Society. Series B. Methodological* 62, 271–292.

- Neumann, M. H., von Sachs, R. (1997). Wavelet thresholding in anisotropic function classes and application to adaptive estimation of evolutionary spectra. *The Annals of Statistics* 25, 38–76.
- Palma, W., Del Pino, G. (1999). Statistical analysis of incomplete long-range dependent data. *Biometrika* 86, 965–972.
- Pelgrum, H., Schmugge, T., Rango, A., Ritchie, J., Kustas, B. (2000). Length-scale analysis of surface albedo, temperature, and normalized difference vegetation index in desert grassland. *Water Resources Research* 36, 1757–1766.
- Percival, D. B. (1995). On estimation of the wavelet variance. *Biometrika* 82, 619–631.
- Percival, D. B., Walden, A. T. (2000). *Wavelet methods for time series analysis*. Cambridge, UK: Cambridge University Press.
- Pichot, V., Gaspoz, J. M., Molliex, S., Antoniadis, A., Busso, T., Roche, F., Costes, F., Quintin, L., Lacour, J. R., Barthélémy, J. C. (1999). Wavelet transform to quantify heart rate variability and to assess its instantaneous changes. *Journal of Applied Physiology* 86, 1081–1091.
- Rybák, J., Dorotovič, I. (2002). Temporal variability of the coronal green-line index (1947–1998). *Solar Physics* 205, 177–187.
- Serroukh, A., Walden, A. T., Percival, D. B. (2000). Statistical properties and uses of the wavelet variance estimator for the scale analysis of time series. *Journal of the American Statistical Association* 95, 184–196.
- Stoica, P., Larsson, E. G., Li, J. (2000). Adaptive filter-bank approach to restoration and spectral analysis of gapped data. *The Astronomical Journal* 163, 2163–2173.
- Sweldens, W. (1997). The lifting scheme: a construction of second generation wavelets. *SIAM Journal on Mathematical Analysis* 19, 511–546.
- Torrence, C., Compo, G. P. (1998). A practical guide to wavelet analysis. *Bulletin of the American Meteorological Society* 79, 61–78.
- Toussoun, O. (1925). Mémoire sur l’histoire du Nil. *Mémoires a l’Institut d’Égypte* 9, 366–404.
- Tsakiroglou, E., Walden, A. T. (2002). From Blackman–Tukey pilot estimators to wavelet packet estimators: a modern perspective on an old spectrum estimation idea. *Signal Processing* 82, 1425–1441.
- Vio, R., Strohmer, T., Wamsteker, W. (2000). On the reconstruction of irregularly sampled time series. *Publications of the Astronomical Society of the Pacific* 112, 74–90.
- Whitcher, B. J., Guttorp, P., Percival, D. B. (2000). Wavelet analysis of covariance with application to atmospheric time series. *Journal of Geophysical Research* 105, 14,941–14,962.

Whitcher, B. J, Byers, S. D., Guttorp, P., Percival, D. B. (2002). Testing for homogeneity of variance in time series: long memory, wavelets and the Nile river. *Water Resources Research* 38, 1054–1070.

Žurbenko, I. G. (1986). *The spectral analysis of time series*. Amsterdam: North–Holland.

Zygmund, A. (1978). *Trigonometric series*. Cambridge, UK: Cambridge University Press.